



NISOC

نگهداشت و افزایش تولید میدان نفتی بینک
سطح الارض

احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



ELECTRICAL LOAD LIST

شماره پیمان:

۰۵۳ - ۰۷۳ - ۹۱۸۴

نسخه	سریال	نوع مدرک	رشته	تسهیلات	صادرکننده	بسته کاری	پروژه
D04	0001	LI	EL	120	PEDCO	GCS	BK

شماره صفحه: ۱ از ۷

طرح نگهداشت و افزایش تولید ۲۷ مخزن

ELECTRICAL LOAD LIST

نگهداشت و افزایش تولید میدان نفتی بینک

Rev.	Date	Purpose of Issue / Status	Prepared by:	Checked by:	Approved by:	CLIENT Approval
D03	Jul.2022	IFA	H.Shakiba	M.Fakharian	M.Mehrshad	
D03	May.2022	IFA	H.Shakiba	M.Fakharian	M.Mehrshad	
D02	Mar.2022	IFA	H.Shakiba	M.Fakharian	M.Mehrshad	
D01	Jan.2022	IFA	H.Shakiba	M.Fakharian	M.Mehrshad	
D00	Nov.2021	IFC	H.Shakiba	M.Fakharian	M.Mehrshad	

Class: 2

CLIENT Doc. Number: F0Z-709066

status:

IDC: Inter-Discipline Check

IFC: Issued For Comment

IFA: Issued For Approval

AFD: Approved For Design

AFC: Approved For Construction

AFP: Approved For Purchase

AFQ: Approved For Quotation

IFI: Issued For Information

AB-R: As-Built for CLIENT Review

AB-A: As-Built -Approved



NISOC

نگهداشت و افزایش تولید میدان نفتی بینک
سطح الارض

احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک

ELECTRICAL LOAD LIST



شماره پیمان:

۰۵۳ - ۰۷۳ - ۹۱۸۴

نسخه	سریال	نوع مدرک	رشته	تسهیلات	صادرکننده	بسته کاری	پروژه
D04	0001	LI	EL	120	PEDCO	GCS	BK

شماره صفحه: ۲ از ۷

REVISION RECORD SHEET

Page	D00	D01	D02	D03	D04
1	X	X	X	X	X
2	X	X	X	X	X
3	X	X	X	X	X
4	X	X	X	X	X
5	X	X	X	X	X
6	X	X	X	X	X
7			X	X	X
8					
9					
10					
11					
12					
13					
14					
15					
16					
17					
18					
19					
20					
21					
22					
23					
24					
25					
26					
27					
28					
29					
30					
31					
32					
33					
34					
35					
36					
37					
38					
39					
40					
41					
42					
43					
44					
45					
46					
47					
48					
49					
50					

Page	D00	D01	D02	D03	D04
51					
52					
53					
54					
55					
56					
57					
58					
59					
60					
61					
62					
63					
64					
65					
66					
67					
68					
69					
70					
71					
72					
73					
74					
75					
76					
77					
78					
79					
80					
81					
82					
83					
84					
85					
86					
87					
88					
89					
90					
91					
92					
93					
94					
95					
96					
97					
98					
99					
100					



تجهه‌داشت و افزایش تولید میدان نفتی بینک
سطح الارض

احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



ELECTRICAL LOAD LIST

شماره پیمان:

۰۵۳-۰۷۳-۹۱۸۴

پروژه

بسته کاری

صادرکننده

تسهیلات

رشته

نوع مدرک

سریال

نسخه

BK

GCS

PEDCO

120

EL

LI

0001

D04

شماره صفحه: ۷ از ۳

Service Type:

N : Normal Load

E : Emergency Load

Load Duty:

C : Continuous Load

I : Intermitant Load

S : Stand By Load

LR/FL: Loacked Rotor / Full Load Current

Load Type:

M: Motor

F: Non-Motor

Definition of API Factor

1.25 for Motor Power < 22kW,

1.15 for Motor Power between, 22kW and 55kW

1.1 for Motor Power > 55kW

Height derating factor can be determined as follows if no manufacturer data is available:

Height Above Sea Level	Height Factor
< 1000 m	1
1000 < Height < 1500 m	0.97
1500 m >	0.94

Coolant (Cooling) Factor is 0.88 according to basic document for motor feeder type.

LV Feeder Type:

F1: Simple 4-Pole MCCB Feeder with Thermal/Magnetic Trips, for I<63A Feeders

F2: Simple 4-Pole MCCB Feeder with Thermal/Magnetic Trips, for 63A=<I<100A Feeders

F3: Simple 4-Pole MCCB Feeder with Thermal/Magnetic Trips, for 100A=<I Feeders

F4: Simple 3-Pole MCCB Feeder with Thermal/Magnetic Trips, for I<63A Feeders

F5: Simple 3-Pole MCCB Feeder with Thermal/Magnetic Trips, for 63A=<I<100A Feeders

F6: Simple 3-Pole MCCB Feeder with Thermal/Magnetic Trips, for 100A=<I Feeders

F7: Simple 2-Pole MCCB Feeder for Feeding Single Phase Loads (Ph+N or 2-Ph)

M1: Direct on Line Motor Starter Feeders for $0.4 \leq P < 4kW$ (Switch Fuse + Contactor + Bimetal + R/L Signaling)

M2: Direct on Line Motor Starter Feeders for $4kW \leq P < 18.5kW$ (Switch Fuse + Contactor + Bimetal + R/L Signaling + R/L Ammeter)

M3: Direct on Line Motor Starter Feeders for $18.5kW \leq P < 30$ (Switch Fuse + Contactor + Bimetal + R/L Signaling + R/L Ammeter (49, 50G, Phase Control))

M4: Direct on Line Motor Starter Feeders for $30kW \leq P$ (Switch Fuse + Contactor + Overload CT + R/L Signaling + R/L Ammeter + Motor Protection Relay (49, 50G, Phase Control))

MV Feeder Type:

C1: 11 KV Incoming Feeder

C2: Outgoing Transformer 2000 KVA

C3: Outgoing Motor Starter <1000 KW

C4: Bus Coupler 11 KV



نگهداشت و افزایش تولید میدان نفتی بینک
سطح الارض
احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



ELECTRICAL LOAD LIST

شماره پیمان:	پروژه	بسته کاری	صادرکننده	تسهیلات	رشته	نوع مدرک	سریال	نسخه
	BK	GCS	PEDCO	120	EL	LI	0001	D04

شماره صفحه: ۷ از ۷

Item NO	Rev	Bus	Equipment Number	Load Description	Service Type	Load Duty	Diversity Factor for Demand Load	NO Phases	Rated Voltage (V)	Load Type	Starting Method	BHP (Kw)	API Factor	Coolant Factor	Height Factor	Mechanical Power (Kw)	Rated Power (Kw)	EFF (%)	Power Factor	Load Factor (%)	LR/FL	Current Normal Operation(A)	Starting Conditions Current (A)	Absorbed Peak Active Power (Kw)	Absorbed Peak Reactive Power (Kvar)	Absorbed Peak Apparent Power (Kva)	Feeder Type
1	D02	GCS-11-SWG-001A	C-2101A	First & Second Stage Gas Compressor A	N	C	1	3	11	M	DOL	932	1.1	0.88	1	1165	1250	95	77	74.6	6	89.7	538.1	981.05	812.928	1274.09	C3
2	D02	GCS-11-SWG-001B	C-2101B	First & Second Stage Gas Compressor B	N	C	1	3	11	M	DOL	932	1.1	0.88	1	1165	1250	95	77	74.6	6	89.7	538.1	981.05	812.928	1274.09	C3
3	D02	GCS-11-SWG-001A	C-2101C	First & Second Stage Gas Compressor C	N	S	0.1	3	11	M	DOL	932	1.1	0.88	1	1165	1250	95	77	74.6	6	89.7	538.1	98.11	81.293	127.41	C3
4	D00	GCS-11-SWG-001B	P-2301A	Fire Water Electric Pump	N	I	0.75	3	3.3	M	DOL	220	1.1	0.88	1	275.00	300	92	82	73.3	6	69.57	417.44	179.35	125.19	218.72	C3
5	D03	GCS-11-SWG-001A	GCS-TR-001	Transformer-001 11/42 KV	N	C	1	3	11	F	-	-	-	-	-	1000	100	80	100.0	1	65.61	-	1000.00	750.00	1250.00	C2	
6	D03	GCS-11-SWG-001B	GCS-TR-002	Transformer-002 11/42 KV	N	C	1	3	11	F	-	-	-	-	-	1000	100	80	100.0	1	65.61	-	1000.00	750.00	1250.00	C2	

GCS-11-SWG-001A					
Continuous		Intermittent		Standby	
Active Power (Kw)	Reactive Power (Kvar)	Active Power (Kw)	Reactive Power (Kvar)	Active Power (Kw)	Reactive Power (Kvar)
1981.05	1562.93	0.00	0.00	98.11	81.29
Power Calculation		Active Power (Kw)	Reactive Power (Kvar)	Apparent power (KVA)	Power Factor
Maximum Normal Running Load		1981.05	1562.93	2523.35	0.79
Peak Load		2079.158	1644.221	2650.73	0.78
Peak Load				2650.728	

GCS-11-SWG-001B					
Continuous		Intermittent		Standby	
Active Power (Kw)	Reactive Power (Kvar)	Active Power (Kw)	Reactive Power (Kvar)	Active Power (Kw)	Reactive Power (Kvar)
1981.05	1562.93	179.35	125.19	0.00	0.00
Power Calculation		Active Power (Kw)	Reactive Power (Kvar)	Apparent power (KVA)	Power Factor
Maximum Normal Running Load		2160.40	1688.11	2741.73	0.79
Peak Load		2160.40	1688.11	2741.73	0.79
Peak Load				2741.725	

The Peak load on 11 Kv switchgear "GCS-11-SWG-001A" is 2650 KVA while demand load on "GCS-11-SWG-001B" is about 2742 KVA.

Fire water Pump will fed from 800 kVA transformer 11/3.3 KV, which will be finalized after power flow calculation.



نگهداشت و افزایش تولید میدان نفتی بینک
سطح الارض
احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



ELECTRICAL LOAD LIST

شماره پیمان:

۰۵۳-۷۳-۹۱۴

پروژه	پسته کاری	صادر کننده	تسهیلات	رشته	نوع مدرک	سریال	نسخه
BK	GCS	PEDCO	120	EL	LI	0001	D04

شماره صفحه: ۵ از ۷

Item NO	Rev	Bus	Equipment Number	Load Description	Service Type	Load Duty	Diversity Factor for Demand Load	NO Phases	Rated Voltage (V)	Load Type	Starting Method	BHP (Kw)	API Factor	Coolant Factor	Height Factor	Mechanical Power (Kw)	Rated Power (Kw)	Eff. (%)	Power Factor	Load Factor (%)	LR/FL	Current Normal Operation(A)	Absorbed Peak Active Power (Kw)	Absorbed Peak Reactive Power (Kvar)	Feeder Type
1	D01	GCS-400-NSWG-001A	AC-2121A	First Stage Air Cooler 21A	N	C	1	3	0.4	M	DOL	10	1.25	0.88	1	14.20	18.5	92.3	84	54.1	7	34.4	10.83	7.00	M3
2	D01	GCS-400-NSWG-001A	AC-2122A	First Stage Air Cooler 22A	N	C	1	3	0.4	M	DOL	10	1.25	0.88	1	14.20	18.5	92.3	84	54.1	7	34.4	10.83	7.00	M3
3	D01	GCS-400-NSWG-001B	AC-2121B	First Stage Air Cooler 21B	N	C	1	3	0.4	M	DOL	10	1.25	0.88	1	14.20	18.5	92.3	84	54.1	7	34.4	10.83	7.00	M3
4	D01	GCS-400-NSWG-001B	AC-2122B	First Stage Air Cooler 22B	N	C	1	3	0.4	M	DOL	10	1.25	0.88	1	14.20	18.5	92.3	84	54.1	7	34.4	10.83	7.00	M3
5	D01	GCS-400-NSWG-001A	AC-2121C	First Stage Air Cooler 21C	N	S	0.1	3	0.4	M	DOL	10	1.25	0.88	1	14.20	18.5	92.3	84	54.1	7	34.4	1.08	0.70	M3
6	D01	GCS-400-NSWG-001A	AC-2122C	First Stage Air Cooler 22C	N	S	0.1	3	0.4	M	DOL	10	1.25	0.88	1	14.20	18.5	92.3	84	54.1	7	34.4	1.08	0.70	M3
7	D01	GCS-400-NSWG-001A	AC-2131A	Second Stage Air Cooler 31A	N	C	1	3	0.4	M	DOL	11	1.25	0.88	1	15.63	18.5	92.3	84	59.5	7	34.4	11.92	7.70	M3
8	D01	GCS-400-NSWG-001A	AC-2132A	Second Stage Air Cooler 32A	N	C	1	3	0.4	M	DOL	11	1.25	0.88	1	15.63	18.5	92.3	84	59.5	7	34.4	11.92	7.70	M3
9	D01	GCS-400-NSWG-001B	AC-2131B	Second Stage Air Cooler 31B	N	C	1	3	0.4	M	DOL	11	1.25	0.88	1	15.63	18.5	92.3	84	59.5	7	34.4	11.92	7.70	M3
10	D01	GCS-400-NSWG-001B	AC-2132B	Second Stage Air Cooler 32B	N	C	1	3	0.4	M	DOL	11	1.25	0.88	1	15.63	18.5	92.3	84	59.5	7	34.4	11.92	7.70	M3
11	D01	GCS-400-NSWG-001A	AC-2131C	Second Stage Air Cooler 31C	N	S	0.1	3	0.4	M	DOL	11	1.25	0.88	1	15.63	18.5	92.3	84	59.5	7	34.4	1.19	0.77	M3
12	D01	GCS-400-NSWG-001A	AC-2132C	Second Stage Air Cooler 32C	N	S	0.1	3	0.4	M	DOL	11	1.25	0.88	1	15.63	18.5	92.3	84	59.5	7	34.4	1.19	0.77	M3
13	D04	GCS-400-NSWG-001E	PK-C-2203A	Instrument & Plant Air Package A	E	C	1	3	0.4	F	-	-	-	-	-	-	50	100	85	100.0	1	84.90	50.00	30.99	F3
14	D04	GCS-400-NSWG-001E	PK-C-2203B	Instrument & Plant Air Package B	E	S	0.1	3	0.4	F	-	-	-	-	-	-	50	100	85	100.0	1	84.90	5.00	3.10	F3
15	D04	GCS-400-NSWG-001A	PK-Dr-2203	Air Dryer Package	N	C	1	3	0.4	F	-	-	-	-	-	-	2	100	85	100.0	1	3.40	2.00	1.24	F1
16	D01	GCS-400-NSWG-001B	PK-Dr-2203B	Air Dryer Package B	N	S	0.1	3	0.4	F	-	-	-	-	-	-	0	100	95	100.0	1	0.00	0.00	0.00	F1
17	D03	GCS-400-NSWG-001A	PK-C-2204	Air Compressor for N2 Package	N	C	1	3	0.4	F	-	-	-	-	-	-	30	100	85	100.0	1	50.94	30.00	18.59	F2
18	D02	GCS-400-NSWG-001A	PK-2204	Nitrogen Package	N	C	1	3	0.4	F	-	-	-	-	-	-	2	100	85	100.0	1	3.40	2.00	1.24	F1
19	D04	GCS-400-NSWG-001A	PK-2201	LP Flare Package	N	C	1	3	0.4	F	-	-	-	-	-	-	22.5	100	95	100.0	1	34.19	22.50	7.40	F2
20	D00	GCS-400-NSWG-001E	IG-2201	LP Flare Ignition Package	E	I	0.75	3	0.4	F	-	-	-	-	-	-	2	100	95	100.0	1	3.04	1.50	0.49	F1
21	D04	GCS-400-NSWG-001B	PK-2207	Corrosion Inhibitor Package	N	C	1	3	0.4	F	-	-	-	-	-	-	2	100	95	100.0	1	3.04	2.00	0.66	F1
22	D04	GCS-400-NSWG-001B	PK-2208	Methanol Injection Package	N	I	0.75	3	0.4	F	-	-	-	-	-	-	0	100	95	100	1	0	0	0	F1
23	D00	GCS-400-NSWG-001B	PK-2101	Dehydration Package	N	C	1	3	0.4	F	-	-	-	-	-	-	20	100	95	100.0	1	30.39	20.00	6.57	F1
24	D04	GCS-400-NSWG-001E	P-2203A	Sump Pump A	E	I	0.75	3	0.4	M	DOL	1	1.25	0.88	1	1.42	2.2	86.8	77	45.45	5.2	4.75	0.86	0.72	M1
25	D04	GCS-400-NSWG-001E	P-2203B	Sump Pump B	E	I	0.75	3	0.4	M	DOL	1	1.25	0.88	1	1.42	2.2	86.8	77	45.45	5.2	4.75	0.86	0.72	M1
26	D04	GCS-400-NSWG-001E	P-2202A	Closed Drain Pump A	E	I	0.75	3	0.4	M	DOL	2.9	1.25	0.88	1	4.12	1.1	83.9	80	263.6	4.7	2.37	2.59	1.94	M1
27	D04	GCS-400-NSWG-001E	P-2202B	Closed Drain Pump B	E	I	0.75	3	0.4	M	DOL	2.9	1.25	0.88	1	4.12	1.1	83.9	80	263.6	4.7	2.37	2.59	1.94	M1
28	D04	GCS-400-NSWG-001A	P-2101A	Slug Pump A	N	I	0.75	3	0.4	M	DOL	7	1.25	0.88	1	9.94	30	92	80	23.3	7	58.83	5.71	4.28	M4
29	D04	GCS-400-NSWG-001B	P-2101B	Slug Pump B	N	I	0.75	3	0.4	M	DOL	7	1.25	0.88	1	9.94	30	92	80	23.3	7	58.83	5.71	4.28	M3
30	D03	GCS-400-NSWG-001A	P-2302A	Fire Water Jockey Pump A	N	I	0.75	3	0.4	F	-	12	1.25	0.88	1	-	20	100	95	60.0	1	30.39	15.00	4.93	F2
31	D03	GCS-400-NSWG-001B	P-2302B	Fire Water Jockey Pump B	N	I	0.75	3	0.4	F	-	12	1.25	0.88	1	-	20	100	95	60.0	1	30.39	15.00	4.93	F2
32	D04	GCS-400-NSWG-001B	P-2209	Potable Water Pump	N	I	0.75	3	0.4	M	DOL	1	1.25	0.88	1	1.42	2.2	86.8	77	45.5	5.2	4.75	0.86	0.72	M1
33	D04	GCS-400-NSWG-001B	P-2206	Diesel Oil Pump	N	I	0.75	3	0.4	M	DOL	0.3	1.25	0.88	1	0.43	2.2	86.8	77	13.6	5.2	4.75	0.26	0.21	M1
34	D04	GCS-400-NSWG-001E	P-2201A	LP Flare K.O. Drum Pump A	E	I	0.75	3	0.4	M	DOL	0.6	1.25	0.88	1	0.85	1.1	83.9	80	54.5	4.7	2.37	0.54	0.40	M1
35	D04	GCS-400-NSWG-001E	P-2201B	LP Flare K.O. Drum Pump B	E	I	0.75	3	0.4	M	DOL	0.6	1.25	0.88	1	0.85	1.1	83.9	80	54.5	4.7	2.37	0.54	0.40	M1
36	D04	GCS-400-NSWG-001A	P-2103A	Glycol Transfer Pump A	N	I	0.75	3	0.4	M	DOL	1	1.25	0.88	1	1.42	1.5	85.6	82	66.7	5	3.08	0.88	0.61	M1
37	D04	GCS-400-NSWG-001B	P-2103B	Glycol Transfer Pump B	N	I	0.75	3	0.4	M	DOL	1	1.25	0.88	1	1.42	1.5	85.6	82	66.7	5	3.08	0.88	0.61	M1
38	D00	GCS-400-NSWG-001B	P-2102	Glycol Manual Pump	N	I	0.75	3	0.4	M	DOL	0.5	1.25	0.88	1	0.71	1.1	83.9	80	45.5	4.7	2.37	0.45	0.34	M1
39	D04	GCS-400-NSWG-001B	P-2104	Glycol Drain Pump	N	I	0.75	3	0.4	M	DOL	0.8	1.25	0.88	1	1.14	1.1	83.9	80	72.7	4.7	2.37	0.72	0.54	M1
40	D01	GCS-400-NSWG-001A	P-2105A	Glycol Sump Pump A	N	I	0.75	3	0.4	M	DOL	0	1.25	0.88	1	0.00	0.75	78.2	74	0.0	4.7	1.87	0.00	0.00	M1
41	D01	GCS-400-NSWG-001B	P-2105B	Glycol Sump Pump B	N	I	0.75	3	0.4	M	DOL	0	1.25	0.88	1	0.00	0.75	78.2	74	0.0	4.7	1.87	0.00	0.00	M1
42	D04	GCS-400-NSWG-001B	GCS-400-CR-01	Main Compressor Crane	N	I	0.75	3	0.4	F	-	-	-	-	-	-	10	100	90	100.0	1	16.04	7.50	3.63	F1
43	D04	GCS-400-NSWG-001A	GCS-400-CR-02	Fire Water Pumps Crane	N	I	0.75	3	0.4	F	-	-	-	-	-	-	5	100	90	100.0	1	8.02	3.75	1.82	F1
44	D04	GCS-400-NSWG-001B	GCS-400-NDP-01	Process Area Normal Distribution Panel	N	C	1	3	0.4	F	-	-	-	-	-	-	20	100	85	100.0	1	33.96	20.00	12.39	F1
45	D04	GCS-400-NSWG-001E	GCS-400-EDP-01	Process Area Emergency Distribution Panel	E	C	1	3	0.4	F	-	-	-	-	-	-	10	100	85	100.0	1	16.98	10.00	6.20	F1
46	D04	GCS-400-NSWG-001A	GCS-400-NDP-02	Utility Area Normal Distribution Panel	N	C	1	3	0.4	F	-	-	-	-	-	-	10	100	85	100.0	1	16.98	10.00	6.20	F1
47	D04	GCS-400-NSWG-001E	GCS-400-EDP-02	Utility Area Emergency Distribution Panel	E	C	1	3	0.4	F	-	-	-	-	-	-	5	100	85	100.0	1	8.49	5.00	3.10	F1
48	D03	GCS-400-NSWG-001B	GCS-400-WS-01	Welding Receptacle (3 Phase) (Process Area)	N	I	0.75	3	0.4	F	-	-	-	-	-	-	35	100	85	100.0	1	59.43	26.25	16.27	F2
49	D03	GCS-400-NSWG-001A	GCS-400-WS-02	Welding Receptacle (3 Phase) (Utility Area)	N	I	0.75	3	0.4	F	-	-	-	-	-	-	35	100	85	100.0	1	59.43	26.25	16.27	F2
50	D02	GCS-400-NSWG-001A	GCS-400-CP01	Cathodic Protection Transformer Rectifier1	N	C	1	3	0.4	F	-	-	-	-	-	-	5	90	100	100.0	1	8.02	5.56	0.00	F1
51	D01	GCS-400-NSWG-001B	GCS-400-CP02	Cathodic Protection Transformer Rectifier2	N	C	1	3	0.4	F	-	-	-	-	-	-	10	90	100	100.0	1	16.04	11.11	0.00	F1
52	D04	GCS-400-NSWG-001E	CTRL- HVAC	HVAC Panel for Control Room	E	C	1	3	0.4	F	-	-	-	-	-	-	150	100	85	100.0	1	254.71	150.00	92.96	F3
53	D01	GCS-400-NSWG-001A	GCS-110-CHG-001	110VDC Charger 1	N	S	0.1	3	0.4	F	-	-	-	-	-	-	20	90	85	100.0	1	37.74	2.22	1.38	F1
54	D04	GCS-400-NSWG-001E	GCS-110-CHG-002	110VDC Charger 2	E	C	1	3	0.4	F	-	-	-	-	-	-	20	90	85	100.0	1	37.74	22.22	13.77	F1
55	D01	GCS-400-NSWG-001A	GCS-24-CHG-001	24VDC Charger 1	N	S	0.1	3	0.4	F	-	-	-	-	-	-	18.5	90	85	100.0	1	34.91	2.06	1.27	F1
56	D04	GCS-400-NSWG-001E	GCS-24-CHG-002	24VDC Charger 2	E	C	1	3	0.4	F	-	-													



نگهداشت و افزایش تولید میدان نفتی بینک
 سطح الارض
 احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



ELECTRICAL LOAD LIST

شماره پیمان:	پروژه	بسته کاری	صادر کننده	تسهیلات	رشته	نوع مدرک	سریال	نسخه	شماره صفحه: 6 از 7
۰۳-۷۳-۹۱۴	BK	GCS	PEDCO	120	EL	LI	0001	D04	

Item NO	Rev	Bus	Equipment Number	Load Description	Service Type	Load Duty	Diversity Factor for Demand Load	NO Phases	Rated Voltage (V)	Load Type	Starting Method	BHP (Kw)	API Factor	Coolant Factor	Height Factor	Mechanical Power (Kw)	Rated Power (Kw)	Eff. (%)	Power Factor	Load Factor (%)	LR/FL	Current Normal Operation(A)	Absorbed Peak Active Power (Kw)	Absorbed Peak Reactive Power (Kvar)	Feeder Type
59	D01	GCS-400-NSWG-001E	GCS-110-UPS-Bypass	110VAC UPS By Pass	E	S	0.1	3	0.4	F	-	-	-	-	-	-	20	90	85	100.0	1	37.74	2.22	1.38	F1
60	D04	GCS-400-NSWG-001E	GCS-400-Non-UPS	Non-UPS Load for Instrument	E	G	±	3	0.4	F	-	-	-	-	-	-	0	100	85	100.0	±	0.00	0.00	0.00	F1
61	D04	GCS-400-NSWG-001B	GCS-400-NDB-CAP	Capacitor Room Normal Lighting Panel	N	G	±	3	0.4	F	-	-	-	-	-	-	0	100	85	100.0	±	0.00	0.00	0.00	F1
62	D02	GCS-400-NSWG-001E	ELP-105	Capacitor Room Emergency Lighting Panel	E	G	±	3	0.4	F	-	-	-	-	-	-	0	100	80	100.0	±	0.00	0.00	0.00	F1
63	D04	GCS-400-NSWG-001A		MOV 1	N	C	1	3	0.4	F	-	-	-	-	-	-	2	100	85	100.0	1	3.40	2.00	1.24	F1
64	D04	GCS-400-NSWG-001B		MOV 2	N	S	0.1	3	0.4	F	-	-	-	-	-	-	2	100	85	100.0	1	3.40	0.20	0.12	F1
65	D01	GCS-400-NSWG-001B		MOV 3	N	G	±	3	0.4	F	-	-	-	-	-	-	0	100	85	100.0	±	0.00	0.00	0.00	F1
66	D01	GCS-400-NSWG-001B		MOV 4	N	G	±	3	0.4	F	-	-	-	-	-	-	0	100	85	100.0	±	0.00	0.00	0.00	F1
67	D04	GCS-400-NSWG-001E	GCS-230-FDP 01	Fire Diesel Panel 01 (Electrical Main Motor)	E	C	1	1	0.23	F	-	-	-	-	-	-	1	100	85	100.0	1	2.95	1.00	0.62	F7
68	D04	GCS-400-NSWG-001E	GCS-230-FDP 02	Fire Diesel Panel 02 (Disel Engine)	E	C	1	1	0.23	F	-	-	-	-	-	-	1	100	85	100.0	1	2.95	1.00	0.62	F7
69	D04	GCS-400-NSWG-001A	MCC-2101A	Auxiliary Panel for Gas Compressor C-2101A	N	C	1	3	0.4	F	-	-	-	-	-	-	25	100	85	100.0	1	42.45	25.00	15.49	F1
70	D04	GCS-400-NSWG-001B	MCC-2101B	Auxiliary Panel for Gas Compressor C-2101B	N	C	1	3	0.4	F	-	-	-	-	-	-	25	100	85	100.0	1	42.45	25.00	15.49	F1
71	D04	GCS-400-NSWG-001B	MCC-2101C	Auxiliary Panel for Gas Compressor C-2101C	N	S	0.1	3	0.4	F	-	-	-	-	-	-	25	100	85	100.0	1	42.45	2.50	1.55	F1
72	D01	GCS-400-NSWG-001E	SPH-01	Space Heater & Lighting for New LV Switchgear	E	C	1	1	0.23	F	-	-	-	-	-	-	2	100	85	100.0	1	5.91	2.00	1.24	F7
73	D01	GCS-400-NSWG-001E	SPH-02	Space Heater & Lighting for MV Switchgear	E	C	1	1	0.23	F	-	-	-	-	-	-	2	100	85	100.0	1	5.91	2.00	1.24	F7
74	D04	GCS-400-NSWG-001B	GCS-400-NDP-CRM	Control Room Normal Distribution Panel	N	C	1	3	0.4	F	-	-	-	-	-	-	30	100	85	100.0	1	50.94	30.00	18.59	F2
75	D04	GCS-400-NSWG-001E	GCS-400-EDP-CRM	Control Room Emergency Distribution Panel	E	C	1	3	0.4	F	-	-	-	-	-	-	23	100	85	100.0	1	39.06	23.00	14.25	F1
76	D04	GCS-400-NSWG-001E	GCS-400-EDB-CAP	Capacitor Room Emergency Lighting Panel	E	G	±	3	0.4	F	-	-	-	-	-	-	0	100	85	100.0	±	0.00	0.00	0.00	F1
77	D04	GCS-400-NSWG-001A	GCS-400-NDP-SWHVAC	Switchgear HVAC Panel	N	C	1	3	0.4	F	-	-	-	-	-	-	38	100	85	100.0	1	64.53	38.00	23.55	F3
78	D04	GCS-400-NSWG-001A	LV-HVAC01	Split Feeder (HVAC Feeder-01 for LV Room)	N	G	±	3	0.4	F	-	-	-	-	-	-	0	100	90	100.0	±	0.00	0.00	0.00	F1
79	D04	GCS-400-NSWG-001B	LV-HVAC02	Split Feeder (HVAC Feeder-02 for LV Room)	N	G	±	3	0.4	F	-	-	-	-	-	-	0	100	90	100.0	±	0.00	0.00	0.00	F1
80	D04	GCS-400-NSWG-001A	MV-HVAC01	Split Feeder (HVAC Feeder-01 for MV Room)	N	G	±	3	0.4	F	-	-	-	-	-	-	0	100	90	100.0	±	0.00	0.00	0.00	F1
81	D04	GCS-400-NSWG-001B	MV-HVAC02	Split Feeder (HVAC Feeder-02 for MV Room)	N	G	±	3	0.4	F	-	-	-	-	-	-	0	100	90	100.0	±	0.00	0.00	0.00	F1
82	D04	GCS-400-NSWG-001A	GAP-HVAC01	Split Feeder (HVAC Feeder-01 for Capacitor Room)	N	G	±	3	0.4	F	-	-	-	-	-	-	0	100	90	100.0	±	0.00	0.00	0.00	F1
83	D04	GCS-400-NSWG-001B	GAP-HVAC02	Split Feeder (HVAC Feeder-02 for Capacitor Room)	N	G	±	3	0.4	F	-	-	-	-	-	-	0	100	90	100.0	±	0.00	0.00	0.00	F1
84	D03	GCS-400-NSWG-001A	CAP-01	Capacitor Bank 1	N	C	1	3	0.4	F	-	-	-	-	-	-	-	100	100	100	1	216.51	-	150	F3
85	D03	GCS-400-NSWG-001B	CAP-02	Capacitor Bank 2	N	C	1	3	0.4	F	-	-	-	-	-	-	-	100	100	100	1	216.51	-	150	F3

GCS-400-NSWG-001A			
Max Intermittent (KW)	Max Standby (KW)	Max Intermittent (KVAR)	Max Standby (KVAR)
35.00	22.22	21.69	13.77

GCS-400-NSWG-001B			
Max Intermittent (KW)	Max Standby (KW)	Max Intermittent (KVAR)	Max Standby (KVAR)
35.00	40.00	21.69	24.79

GCS-400-NSWG-001E			
Max Intermittent (KW)	Max Standby (KW)	Max Intermittent (KVAR)	Max Standby (KVAR)
3.46	50.00	2.59	30.99



GCS-400-NSWG-001A					
Continuous		Intermittent		Standby	
Active Power (Kw)	Reactive Power (Kvar)	Active Power (Kw)	Reactive Power (Kvar)	Active Power (Kw)	Reactive Power (Kvar)
182.56	104.34	51.58	27.91	8.83	5.59
Power Calculation		Active Power (Kw)	Reactive Power (Kvar)	Apparent power (KVA)	Power Factor
Maximum Normal Running Load (Demand)		234.14	132.25	268.91	0.87
Peak Load		242.970	137.837	279.34	0.87
Peak Load With 20% Spare (KVA)				335.214	

GCS-400-NSWG-001B					
Continuous		Intermittent		Standby	
Active Power (Kw)	Reactive Power (Kvar)	Active Power (Kw)	Reactive Power (Kvar)	Active Power (Kw)	Reactive Power (Kvar)
153.61	83.10	57.62	31.52	6.70	4.15
Power Calculation		Active Power (Kw)	Reactive Power (Kvar)	Apparent power (KVA)	Power Factor
Maximum Normal Running Load (Demand)		211.23	114.63	240.33	0.88
Peak Load		217.93	118.78	248.20	0.88
Peak Load With 20% Spare (KVA)				297.841	

GCS-400-NSWG-001E					
Continuous		Intermittent		Standby	
Active Power (Kw)	Reactive Power (Kvar)	Active Power (Kw)	Reactive Power (Kvar)	Active Power (Kw)	Reactive Power (Kvar)
326.78	202.52	9.49	6.62	7.22	4.48
Power Calculation		Active Power (Kw)	Reactive Power (Kvar)	Apparent power (KVA)	Power Factor
Maximum Normal Running Load		336.26	209.14	395.99	0.85
Peak Load		343.49	213.61	404.49	0.85
Peak Load With 20% Spare (KVA)				485.389	

Total Peak Load on LV Switchgear			
Active Power (Kw)	Reactive Power (Kvar)	Apparent power (KVA)	Power Factor
804.39	470.23	931.75	0.8633
Peak Load		1118.100	

- For each LV switchgear A & B, a separate transformer is needed to supply normal & emergency power. So the sum of apparent power will be about 1142KVA, which 2 transformers 1250 KVA are required.
- Size of transformers shall be finalized in load flow and motor starting study.
- Power factor has been calculated while all capacitor banks are out of service.

 NISOC	نگهداشت و افزایش تولید میدان نفتی بینک سطح الارض								
	احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک							ELECTRICAL LOAD LIST	
شماره پیمان:	پروژه	بسته کاری	صادرکننده	تسهیلات	رشته	نوع مدرک	سریال	نسخه	شماره صفحه: ۷ از ۷
۰۵۳ - ۰۷۳ - ۹۱۸۴	BK	GCS	PEDCO	120	EL	LI	0001	D04	

1. Mechanical Power (KW): Mechanical Power for Motors = BHP(KW) x API Factor / (Cooling Factor x Height Factor)

2. Rated Power(KW): Rated Power = The Nearest Size of The Equipment to Mechanical Power of Motors

3. Load Factor(%): Load Factor = (BHP/Rated Power) x 100

4. Normal Operation(A): Normal Operation (A) = Rated Power / (Sqrt(3) x Nominal Voltage x cosØ)

5. Starting Current(A): Starting Current(A) = (LR/LF) x Normal Current

6. Electrical Power Demand (KW):

Electrical Absorbed Power Demand (KW) = BHP(KW) x Diversity Factor / Efficiency

Electrical Absorbed Power Demand (KW) = Rated Power(KW) x Diversity Factor / Efficiency

7. Electrical Reactive Power Demand (KVAR):

Electrical Reactive Power Demand (KVAR) = Electrical Absorbed Power Demand (KW) x Tangent(Ø)

For "Electrical Demand" calculation, following "Diversity Factors" has been considered (based on peak loads):

Continuous: 100% Diversity factor.

Intermittent: Normally less than 12 hours/day, As generally 75%

Standby: Spare/Backup drives or systems, As generally 10% or biggest standby load (which is bigger)

Notes

1- Electrical heat tracing for compressor will be supplied from Auxiliary MCC