



#### احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک

شماره پیمان:

 $\bullet \Delta \tau = \bullet V \tau - 91 \lambda \tau$ 

TBE FOR EXISTENT MV SWITCHGEAR EXPANSION & RCP
--

 نسخه
 سریال
 نوع مدر ک
 رشته
 تسهیلات
 صادر کننده
 بسته کاری
 پروژه

 BK
 GCS
 PEDCO
 120
 EL
 TB
 0003
 D01

شماره صفحه : ۱ از ۲۸

# طرح نگهداشت و افزایش تولید ۲۷ مخزن

## **TBE For Existent MV Switchgear Expansion & RCP**

نگهداشت و افزایش تولید میدان نفتی بینک

Feb. 2024 Nov. 2023 Date	IFI IFI Purpose of Issue/Status	H.Shakiba H.Shakiba Prepared by:	M.Fakharian M.Fakharian Checked by:	S.Faramarzpour S.Faramarzpour Approved by:	Client Approval
Feb. 2024	IFI	H.Shakiba	M.Fakharian	S.Faramarzpour	

Class:3 Client Doc. Number: F0Z-709332

Status:

IDC: Inter-Discipline Check
IFC: Issued For Comment
IFA: Issued For Approval
AFD: Approved For Design
AFC: Approved For Construction
AFP: Approved For Purchase
AFQ: Approved For Quotation
IFI: Issued For Information
AB-R: As-Built for Client Review

AB-A: As-Built -Approved



## احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:

TBE FOR EXISTENT MV SWITCHGEAR EXPANSION & RCP

· 24 - · 74 - 9114

پروژه	بسته کاری	صادر کننده	تسهيلات	رشته	نوع مدرك	سريال	نسخه
BK	GCS	PEDCO	120	EL	TB	0003	D01

شماره صفحه: ۲ از ۲۸

#### **REVISION RECORD SHEET**

			REVISIO							
PAGE	D00	D01	D02	D03	D04					
1	Х	Х								
2	Х	X								
3	Х	X								
4	Х	Χ								
5	Х	Х								
6	Х	Х								
7	Х	Х								
8	Х	Χ								
9	Х	Х								
10	Х	Х								
11	Х	Х								
12	Х	Х								
13	Х	Х								
14	Х	Х								
15	Х	Х								
16	Х	Х								
17	Х	Х								
18	Х	Х								
19	Х	Х								
20	Х	Х								
21	Х	Х								
22	Х	Х								
23	Х	Х								
24	Х	Х								
25	Х	Х								
26	Х	Х								
27	Х	Х								
28	Х	Х								
29										
30	1									
31										
32	1									
33	1									
34										
35	<u> </u>									
36	1									
37	1									
38	1									
39	1									
40	1									
41	1									
42	1									
43	<u> </u>									
44	†									
45	†									
46	1									
47	†									
48	1									
49	1									
50	1									

PAGE	D00	D01	D02	D03	D04
51					
52					
53					
54					
55					
56					
57					
58					
59					
60					
61					
62					
63					
64					
65					
66					
67					
68					
69					
70					
71					
72					
73					
74					
75					
76					
77					
78					
79					
80	1				
81					
82					
83					
84 85					
86					
87					
88	<del>                                     </del>				
89	<del>                                     </del>				
90					
91	<del>                                     </del>				
92					
93					
94	<u> </u>				
95					
96	<u> </u>				
97					
98					
99					
100					
	1	1		<u> </u>	1





## احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک

شماره پیمان: TBE FOR EXISTENT MV SWITCHGEAR EXPANSION & RCP نوع مدرك پروژه بسته کاری صادر کننده سريال · ۵۳ - · ۷۳ - 9 1 1 4 BK GCS PEDCO EL TBE 120 0003 D01

شماره صفحه: ۳ از ۲۸

		Т	TBE for <u>11 KV</u> Switchg	ear				
MR Item	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)  Description	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
1. E	nvironmental Data (Process Basis Design, BK-G	NRAL-PEDCO-000-PR-DB-0001)						
1.1	Name of Project / Plant	Binak Oilfield in Bushehr Province	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.2	Ambient Temperature (Min/Max)	Min ~ Max: +5 ~ +52°C	Oo1 Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.3	Max.Design Temperature:	52 °c	Confirmed	Ok	40 °c	С	Confirmed	Ok
1.4	Max. Sun Temperature:	+ 85 °c	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.5	Max.Relative Humidity:	100%	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.6	Mean Sea Level	12.5 m Above Sea Level	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.7	Seismic Factor	0.3g	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.8	Max. Wind Velocity(Max)	120 km/hr	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2. S	witchgear							
2.1	Manufacturer	By Vendor	Pars Tableau/DNF4	Ok	Runin Sanat Gostar	Ok	Confirmed	Ok
2.2	Standard(s)	IPS-M-EL-144(4), IPS-E-EL-100(1), BK-GNRAL-PEDCO-000-EL-SP-0002	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.3	Quantity	8 Feeders of Ougoing, Type C2 & C3	Confirmed	Ok	ACC to SLD	Ok	Confirmed	Ok
2.4	Service	Expansion of Exsiting MV Switchgear from Both Side	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.5	Tag Number	GCS-11-SWG-001A/B	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.6	Applicable SLD	BK-GCS-PEDCO-120-EL-SL-0001 BK-GCS-PEDCO-120-EL-SL-0003 BK-GCS-PEDCO-120-EL-DG-0001	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.7	Location	Indoor	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.8	Type and Construction	Metal Clad, Withdrawable	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.9	Rated Voltage & Variation	11 kV ± 10 %	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.10	Rated Frequency & Variation	50 Hz ± 5 %	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.11	No. of Phases	3 PH	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.12	Rated Insulation Levels between earth & phase • One Minute Power Frequency	28 KV	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok



## احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:		TBE FOR EXISTENT MV SWITCHGEAR EXPANSION & RCP									
۰۵۳ - ۷۷۳ - ۹۱۸۴	پروژه	بسته کاری	صادركننده	تسهيلات	رشته	نوع مدر ک	سر يال	نسخه	l		
	ВК	GCS	PEDCO	120	EL	TBE	0003	D01	i		

شماره صفحه: ۴ از ۲۸

T	BE for	<u>11</u>	KV	Switchge	ar

	The for 11 KV Switchgear											
MR	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status				
Item	Description											
	Withstand Voltage (RMS)  • One Minute Power Frequency Withstand Voltage of Aux. Circuit (RMS)  • Impulse Withstand Voltage (Peak)	2 KV 75 KV			N.A 75 Kv							
2.13	Rated Normal Current of Busbars	1600 A	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
2.14	Rated Short Time Current of Busbar	25 kA; 1 sec	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
2.15	Rated Peak Withstand Current	63 kA	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
2.16	Busbars:  • Material  • Main Horizontal Bus Cross Section Area  • Main Vertical Bus Cross Sectional Area  • Earth Bus Cross Sectional Area  • Busbars Color & Joints	Copper (Flame Retardant Non-Hygroscopic)  Vendor to Advise  Vendor to Advise  Vendor to Advise  Silver Plated	Confirmed	Ok	Confirmed  After Contract After Contract After Contract Confirmed	Ok	Confirmed	Ok				
2.17	Maximum Tolerable Temperature Rise	Acc. to IEC62271 IPS-M-EL-144(4)	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
2.18	Rated Voltage for Control And Protection Circuits	110 V DC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
2.19	Rated Voltage for Space Heaters and Panel Lighting	400 / 230 VAC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
2.20	Enclosure	Withdrawable Metal Clad, Compartmented	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
2.21	Degree of Protection by Enclosure	External: IP 42, Internal: IP 20, Internal partitions between functional units and shutters for bus bar & cable side: IP 4X	Confirmed	Ok	Ecternal:IP41 & other Confirmed	С	IP41	С				
2.22	Installation	Floor Self-Standing, Side by Side	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
2.23	Rear / Front Access	Rear and Front Access	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
2.24	Top / Bottom Cable Entry	Cables: Bottom Entry	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
2.25	Sheet Steel Thickness, Fram & Walls	Minimum 2.5 mm	Minimum 2. mm	Ok	Confirmed	Ok	Confirmed	Ok				
2.26	Paint	Electrostatic Powder	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
2.27	Color finish	RAL 7032	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
2.28	Routine Tests	Required (Withstand tests and reports as per IEC 62271-200 or IEC 298, IEC 60694, IPS-M-EL-144 (4) and Specification)	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				



## احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:	TBE FOR EXISTENT MV SWITCHGEAR EXPANSION & RCP								
۰۵۳ - ۰۷۳ — ۹۱۸۴	پروژه	بسته کاری	صادركننده	تسهيلات	رشته	نوع مدرک	سر يال	نسخه	
	ВК	GCS	PEDCO	120	EL	TBE	0003	D01	

شماره صفحه: ۵ از ۲۸

		T	BE for <u>11 KV</u> Switchge	ar				
MR Item	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)  Description	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
2.29	Type Tests	Test certificates of the SWGR type as per IEC62271-200 or IEC 298, IEC60694, and IPS-M-EL-144 (4)	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.30	Overall Dimensions (HxWxD) [mm]	Vendor to Advise	According to Technical Offer	Ok	After Contract	Ok	Confirmed	Ok
2.31	Total Weight [kg]	Vendor to Advise	According to Technical Offer	Ok	After Contract	Ok	Confirmed	Ok
2.32	Overall Dimensions of 1 Cubicle (HxWxD)	Vendor to Advise	According to Technical Offer	Ok	After Contract	Ok	Confirmed	Ok
2.33	Dynamic Load of One Cubicle [kg]	Vendor to Advise	According to Technical Offer	Ok	After Contract	Ok	Confirmed	Ok
3. M	IV Circuit Breaker							
3.1	Manufacturer	Vendor to Advise	Hyundai/South Korea	Ok	Pars Switch		Confirmed	Ok
3.2	Standard	IEC62271-100	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.3	Туре	Vacuum	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.4	Fixed/ Withdrawable	Withdrawable	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.5	Rated Voltage	12 kV ± 10 %	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.6	Rated Frequency	50 Hz ± 5 %	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.7	No. Of Phases and Poles	3-Phase	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.8	Rated Insulation Levels between earth and phase  One Minute Power Frequency Withstand Voltage (RMS)  One Minute Power Frequency Withstand Voltage of Aux. Circuit (RMS)  Impulse Withstand Voltage (Peak)	28 KV 2 KV 75 KV	Confirmed	Ok	Confirmed N.A 75 KV	Ok	Confirmed	Ok
3.9	Rated Normal Current	630 A	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.10	Rated Short Time Current	25 kA; 1 sec	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.11	Rated Peak Withstand Current	62.5 kA	Confirmed	Ok	63 KA	Ok	Confirmed	Ok
3.12	Rated Short Circuit Breaking Current	Vendor to Advise	According to Catalogue	Ok	25 KA	Ok	Confirmed	Ok
3.13	Rated Short Circuit Making Current	Vendor to Advise	According to Catalogue	Ok	63 KA	Ok	Confirmed	Ok
3.14	Maximum Tolerable Temperature Rise	Acc. to IEC62271-100	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok



## احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:		TBE FOR EXISTENT MV SWITCHGEAR EXPANSION & RCP									
۴۸۱۶ – ۳۷۰ – ۳۵۰	پروژه	بسته کاری	صادر کننده	تسهيلات	رشته	نوع مدرک	سر يال	نسخه			
	ВК	GCS	PEDCO	120	EL	TBE	0003	D01			

شماره صفحه: ۶ از ۲۸

MR	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)  Description	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
Item	-							
3.15	Design Temperature Rise	Acc. to IEC62271-100	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.16	Operating Mechanism	Motor & Hand operated Spring Charged Stored Energy Mechanism	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.17	Release type	Shunt Trip	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.18	Rated Operating Sequence	O-0.3S-CO-3MIN-CO	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.19	Rated Voltage of Auxiliary Equipment	110V DC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.20	Rated Operating Voltage of Releases	110V DC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.21	Rated Operating Voltage of Charging Motors	110V DC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.22	Voltage Tolerances for Auxiliary Apparatus:     Trip Circuit     Close Circuit     Motor Running     Motor at the Instant of Start	70%-110% 85%-110% 85%-110% 70%-110%	Confirmed	Ok	After Contract	Ok	Confirmed	Ok
3.23	Power consumption of Auxiliary Apparatus:[W]  • Trip Circuit  • Closed Circuit  • Charging motor  • Under voltage release  • Multifunction relay  • Transducers	110V DC  Vendor to Advise	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.24	<ul> <li>1 C.B. Open/Close Auxiliary Contacts:</li> <li>No. Of Make Contacts</li> <li>No. Of Break Contacts</li> <li>Rated Voltage</li> <li>Rated Current at 110V DC</li> <li>Breaking Current at 110V DC</li> </ul>	6 6 110V DC VTA VTA	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.25	Truck Position Auxiliary Contacts:  No of Make Contacts  No of Break Contacts  Rated Voltage  Rated Current at 110V DC  Breaking Current at 110V DC	1NO + 1NC 1NO + 1NC 110V DC VTA VTA	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.26	Routine Tests	IEC62271-100	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.27	Type Tests	IEC62271-100	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok



## احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:		TBE FOR EXISTENT MV SWITCHGEAR EXPANSION & RCP									
۰۵۳ - ۰۷۳ – ۹۱۸۴	پروژه	بسته کاری	صادركننده	تسهيلات	رشته	نوع مدرک	سر يال	نسخه			
· 61 - · 11 (17)	ВК	GCS	PEDCO	120	EL	TBE	0003	D01			

شماره صفحه: ۷ از ۲۸

			TBE for 11 KV Switchge	ear				
MR	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
Item	Description							
4.1	Manufacturers Name	Vendor to Advise	Pars Shar/Iran	Ok	Pars Shar	Ok	Confirmed	Ok
4.2	Standard	IEC60044-2	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.3	Туре	Epoxy Cast Resin	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.4	Fixed/Withdrawable	Withdrawable	Tilting	N	Confirmed	Ok	Confirmed	Ok
4.5	Highest System Voltage	12 kV	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.6	Rated Frequency	50 Hz	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.7	No. of Phase	Single Phase	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.8	Rated Primary Voltage [kV]	11/√3 kV	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.9	Rated Secondary Voltage [V]	110/√3 V	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.10	Rated Insulation Levels between earth and phase  One Minute Power Frequency Withstand Voltage (RMS)  One Minute Power Frequency Withstand Voltage of Aux. Circuit (RMS)  Impulse Withstand Voltage (Peak)	$28 \text{ kV} / \sqrt{3}$ $2 \text{ kV} / \sqrt{3}$ $75 \text{ kV} / \sqrt{3}$	Confirmed	Ok	Confirmed  N.A  Confirmed	Ok	Confirmed	Ok
4.11	System Earthing	TNS	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.12	Rated Voltage Factor	Vendor to Advise	According to Catalogue	Ok	After Contract	Ok	Confirmed	Ok
4.13	Rated Burden	Vendor to Advise	According to Catalogue	Ok	After Contract	Ok	Confirmed	Ok
4.14	Accuracy Class: • for Protection (with separate Winding) • for Measuring (with separate Winding)	CL. 3P 1.0	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.15	Insulation Class & Temperature Rise	Class E, Temp. Rise Class Y	Confirmed	Ok	Insulation (Class A)/ Temperature Rise (N.A)	С	Confirmed	Ok
5. M	IV Current Transformers				1			
5.1	Manufacturer's Name	Vendor to Advise	Pars Shar/Iran	Ok	Pars Shar	Ok	Confirmed	Ok
5.2	Standard	IEC60044-1	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
5.3	Туре	Dry Type	Confirmed	Ok	Resin Type	Ok	Confirmed	Ok
5.4	Highest System Voltage	11 kV	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok



#### نگهداشت و افزایش تولید میدان نفتی بینک سطح الارض

## احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:			TBE FOR EXIS	STENT MV SWITCHGE	AR EXPANSION & R	CP			Г
۰۵۳ - ۰۷۳ — ۹۱۸۴	پروژه	بسته کاری	صادر كننده	تسهيلات	رشته	نوع مدرک	سر يال	نسخه	
· ω1 = · / 1	ВК	GCS	PEDCO	120	EL	TBE	0003	D01	1

شماره صفحه: ۸ از ۲۸

			TBE for <u>11 KV</u> Switchge	ear				
MR Item	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003) Description	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
5.5	Rated Frequency	50 Hz	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
5.6	Rated Secondary Current:	1 A / 5 A According to SLD	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
5.7	Rated Continuous Thermal Current	1.2 x Rated primary current	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
5.8	Rated Short Time, Current:	25 kA, 1 Sec	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
5.9	Rated Dynamic Current:	63 kA	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
5.10	Rated Burden	Vendor to Advise	According to Catalogue	Ok	After Contract	Ok	Confirmed	Ok
5.11	Rated Transformation Ratio and No. of Cores	According to Single Line Diagram	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
5.12	Accuracy Class:  • Measuring  • Protection	Class 1: Class 1FS5 Class X: where required Class 5P20 protections	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
5.13	Routine Tests	IEC60044-1	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
5.14	Type Tests	IEC60044-1	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
5.15	Rated Insulation Levels between earth and phase  One Minute Power Frequency Withstand Voltage (RMS)  One Minute Power Frequency Withstand Voltage of Aux. Circuit (RMS)  Impulse Withstand Voltage (Peak)	$28 \text{ kV} / \sqrt{3}$ $2 \text{ kV} / \sqrt{3}$ $75 \text{ kV} / \sqrt{3}$	Confirmed	Ok	Confirmed  N.A  Confirmed	Ok	Confirmed	Ok
6. E	arth Switch							
6.1	Manufacturer's Name	Vendor to Advise	Parstableau/Iran	Ok	Runin Sanat	Ok	Confirmed	Ok
6.2	Manufacturer's Type Designation	Vendor to Advise	Manual	Ok	After Contract	Ok	Confirmed	Ok
6.3	Standard	IEC62271-102	Confirmed	Ok	After Contract	Ok	Confirmed	Ok
6.4	Туре	Make Proof	Confirmed	Ok	After Contract	Ok	Confirmed	Ok
6.5	Number of Phase	3	Confirmed	Ok	After Contract	Ok	Confirmed	Ok
6.6	Frequency	50 Hz	Confirmed	Ok	After Contract	Ok	Confirmed	Ok
6.7	Rated Voltage	11 kV	Confirmed	Ok	After Contract	Ok	Confirmed	Ok
6.8	Rated Lighting Impulse Withstand Voltage	75 kV	Confirmed	Ok	After Contract	Ok	Confirmed	Ok



## احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:			TBE FOR EXIS	STENT MV SWITCHGE	AR EXPANSION & RO	TBE FOR EXISTENT MV SWITCHGEAR EXPANSION & RCP									
۹۱۸۴ - ۲۷۰ - ۹۱۸۴	پروژه	بسته کاری	صادر کننده	تسهيلات	رشته	نوع مدرك	سريال	نسخه							
- ωτ = . ττ ττλι	BK	GCS	PEDCO	120	EL	TBE	0003	D01							

شماره صفحه: ۹ از ۲۸

	TBE for 11 KV Switchgear											
MR Item	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status				
	<b>Description</b>	20111		01	10.00	0.1	G. C. I	0.1				
6.9	Rated 1 Minute Power Frequency Voltage	28 kV	Confirmed	Ok	After Contract	Ok	Confirmed	Ok				
6.10	Rated Short Time (1s) Current	25 kA	Confirmed	Ok	After Contract	Ok	Confirmed	Ok				
6.11	Rated Peak Withstand Current	62.5 kA	Confirmed	Ok	After Contract	Ok	Confirmed	Ok				
6.12	Rated Short Circuit Making Current	62.5 kA	Confirmed	Ok	After Contract	Ok	Confirmed	Ok				
6.13	Actuation Mechanism	Pre-tension Spring	Confirmed	Ok	After Contract	Ok	Confirmed	Ok				
6.14	No. of Auxiliary Contacts (Min.)	2NO + 2NC	Confirmed	Ok	After Contract	Ok	Confirmed	Ok				
6.15	Aux. Contacts Rated Voltage	110V DC	Confirmed	Ok	After Contract	Ok	Confirmed	Ok				
6.16	Aux. Contacts Rated Current	1A	Confirmed	Ok	After Contract	Ok	Confirmed	Ok				
6.17	Interlocks	According (but not limited) to Appendix B of IPS-M-EL-144 (4) specifically:  To prevent closure of Earth Switch when CB is not in Test or withdraw position  To prevent Insertion of CB when Earth Switch is connected.  To prevent connection of Earth Switch when upstream Switch is not open i.e. electromagnetic coil (only for incoming)	Confirmed	Ok	After Contract	Ok	Confirmed	Ok				
6.18	Routine Tests	IEC62271-102	Confirmed	Ok	After Contract	Ok	Confirmed	Ok				
6.19	Type Tests (Certificates)	IEC62271-102	Confirmed	Ok	After Contract	Ok	Confirmed	Ok				
7. M	otor Feeder Protection Relay											
7.1	Manufacturer's Name	Vendor to Advise	Schneider/France	Ok	Schneider	Ok	Confirmed	Ok				
7.2	Manufacturer's Type Designation	Vendor to Advise	P3M32 & P3U20	Ok	ACC to Technical Proposal	Ok	Confirmed	Ok				
7.3	Туре	Digital Multi-Function Relay + Display with adjustment Menu	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
7.4	Installation	Flush Mounted	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
7.5	Included Protection (ANSI Codes)	50, 51, 46, 51LR, 49, 66, 50G, 51G, 26, 87M, 86 (Separate Relay)	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
7.6	Rated Current [A]	5	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
7.7	Rated Frequency [Hz]	50 Hz	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				



## احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:			TBF FOR FXIS	STENT MV SWITCHGE	AR FXPANSION & RO	CP.			T
	پروژه	بسته کاری	صادر کننده	تسهيلات	ر شته	نوع مدر ک	سويال	نسخه	
• ۵۳ - • ۷۳ - 9 ۱ ۸ ۴	ВК	GCS	PEDCO	120	EL	TBE	0003	D01	

شماره صفحه : ۱۰ از ۲۸

		T	<mark>BE for <u>11 KV</u> Switchg</mark> e	ear				
MR Item	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)  Description	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
7.8	Burden [VA]	Vendor to Advise	According to Catalogue	Ok	After Contract	Ok	Confirmed	Ok
7.9	Overload Capability Of Current Path	100xIn < 1 Sec.	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.10	Rated Voltage Auxiliary Voltage [V]	110V DC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.11	Auxiliary Voltage Permissible Range [V]	Min. ± 15% of Un	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.12	Power Consumption [W]	Vendor to Advise	Confirmed	Ok	After Contract	Ok	Confirmed	Ok
7.13	Trip Relay Contacts	2NO + 2NC at least	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.14	Alarm Relay Contacts	2NO + 2NC at least	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.15	Auxiliary Contacts Ratings  Contacts Voltage Rating [V]  Contacts Rated Continuous Current	110V DC Vendor to Advise	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.16	Ingress Protection	IP42	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.17	Routine Tests	IEC 255	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.18	Type Tests (Certificates)	IEC 255	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8. T	ransformer Feeder Protection Relay							
8.1	Manufacturer's Name	Vendor to Advise	Schneider/France	Ok	Schneider	Ok	Confirmed	Ok
8.2	Manufacturer's Type Designation	Vendor to Advise	P3U20	Ok	ACC to Technical Proposal	Ok	Confirmed	Ok
8.3	Туре	Digital Multi-Function Relay + Display with adjustment Menu	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.4	Installation	Flush Mounted	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.5	Included Protection (ANSI Codes)	50, 51, 51N,50G (Separate Relay)	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.6	Rated Current [A]	5	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.7	Rated Frequency [Hz]	50 Hz	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.8	Burden [VA]	Vendor to Advise	According to Catalogue	Ok	After Contract	Ok	Confirmed	Ok
8.9	Overload Capability Of Current Path	100xIn < 1 Sec.	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.10	Rated Voltage Auxiliary Voltage [V]	110V DC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok



# HIRGAN ENERGY

#### احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک

TBE FOR EXISTENT MV SWITCHGEAR EXPANSION & RCP شماره پیمان: بسته کاری صادر كننده نوع مدرك پروژه تسهيلات سريال · 27 - · 77 - 9114 BK GCS PEDCO 120 EL TBE 0003 D01

شماره صفحه : ۱۱ از ۲۸

		Т	BE for <u>11 KV</u> Switchge	ar				
MR	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
Item	Description							
8.11	Auxiliary Voltage Permissible Range [V]	Min. ± 15% of Un	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.12	Power Consumption [W]	Vendor to Advise	Confirmed	Ok	After Contract	Ok	Confirmed	Ok
8.13	Trip Relay Contacts	2NO + 2NC at least	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.14	Alarm Relay Contacts	2NO + 2NC at least	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.15	Auxiliary Contacts Ratings  • Contacts Voltage Rating [V]  • Contacts Rated Continuous Current	110V DC Vendor to Advise	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.16	Ingress Protection	IP42	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.17	Routine Tests	IEC 255	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.18	Type Tests (Certificates)	IEC 255	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
9. S <sub>]</sub>	pare Part							
9.1	Commissioning Spare Parts according to attach 22 of MR	Yes	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
9.2	Two year Operation Spare Parts according to attach 22 of MR	Yes	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok

#### STATUS LEGENDS:

A=Acceptable

N=Not Acceptable

N/A=Not Applicable

INA=Information Not Available

C=Clarification is Required

CA= Conditionally Acceptable

M = Requirement is Mandatory



# احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:			TBE FOR EXISTENT MV SWITCHGEAR EXPANSION & RCP										
۰۵۳ - ۲۷۳ – ۹۱۸۴	پروژه	بسته کاری	صادر كننده	تسهيلات	رشته	نوع مدرک	سر يال	نسخه					
· W1 · +1 · +1/41	ВК	GCS	PEDCO	120	EL	TBE	0003	D01					

شماره صفحه : ۱۲ از ۲۸

		TBE for <u>3.3 KV</u> Sw	vitchgear (Starter Panel	of Fire Wate	r Pump)			
MR	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
Item	Description							
1. E	nvironmental Data (Process Basis Design, BK-G	NRAL-PEDCO-000-PR-DB-0001)						
1.1	Name of Project / Plant	Binak Oilfield in Bushehr Province	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.2	Ambient Temperature (Min/Max)	Min ~ Max: +5 ~ +52°C	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.3	Max.Design Temperature:	52 °c	Confirmed	Ok	40 °c	С	Confirmed	Ok
1.4	Max. Sun Temperature:	+ 85 °c	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.5	Max.Relative Humidity:	100%	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.6	Mean Sea Level	12.5 m Above Sea Level	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.7	Seismic Factor	0.3g	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.8	Max. Wind Velocity(Max)	120 km/hr	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2. Sv	witchgear							
2.1	Manufacturer	By Vendor	Parstableau/DNF4	Ok	Runin Sanat Gostar	Ok	Confirmed	Ok
2.2	Standard(s)	IPS-M-EL-144(4), IPS-E-EL-100(1), BK-GNRAL-PEDCO-000-EL-SP-0002	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.3	Quantity	1 Feeder of Ougoing, Type C3	Confirmed	Ok	Acc to SLD	Ok	Confirmed	Ok
2.4	Service	ACC to General Arrangement	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.5	Tag Number	GCS-3.3-SWG-001	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.6	Applicable SLD	BK-GCS-PEDCO-120-EL-SL-0001 BK-GCS-PEDCO-120-EL-SL-0003 BK-GCS-PEDCO-120-EL-DG-0001	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.7	Location	Indoor	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.8	Type and Construction	Metal Clad, Withdrawable	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.9	Rated Voltage & Variation	11 kV ± 10 %	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.10	Rated Frequency & Variation	50 Hz ± 5 %	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.11	No. of Phases	3 PH	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok



111P - 770 - 711F

#### نگهداشت و افزایش تولید میدان نفتی بینک سطح الارض

# احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:		TBE FOR EXISTENT MV SWITCHGEAR EXPANSION & RCP						
ç.	پروژه	بسته کاری	صادر کننده	تسهيلات	رشته	نوع مدرک	سر يال	نسخه
1	BK	GCS	PEDCO	120	FI	TRF	0003	D01

شماره صفحه : ۱۳ از ۲۸

TBE for 3.3 KV Switchgear (Start	er Panel of Fire Water Pump)
----------------------------------	------------------------------

MR	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
Item	Description							
2.12	Rated Insulation Levels between earth and phase  One Minute Power Frequency Withstand Voltage (RMS)  One Minute Power Frequency Withstand Voltage of Aux. Circuit (RMS)  Impulse Withstand Voltage (Peak)	10 KV 2 KV 40 KV	Confirmed	Ok	Confirmed N.A 40 Kv	Ok	Confirmed	Ok
2.13	Rated Normal Current of Busbars	630 A	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.14	Rated Short Time Current of Busbar	25 kA; 1 sec	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.15	Rated Peak Withstand Current	63 kA	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.16	Busbars:  • Material  • Main Horizontal Bus Cross Section Area  • Main Vertical Bus Cross Sectional Area  • Earth Bus Cross Sectional Area  • Busbars Color & Joints	Copper (Flame Retardant Non-Hygroscopic)  Vendor to Advise  Vendor to Advise  Vendor to Advise  Silver Plated	Confirmed	Ok	Confirmed After Contract After Contract After Contract Confirmed	Ok	Confirmed	Ok
2.17	Maximum Tolerable Temperature Rise	Acc. to IEC62271 IPS-M-EL-144(4)	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.18	Rated Voltage for Control And Protection Circuits	110 V DC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.19	Rated Voltage for Space Heaters and Panel Lighting	400 / 230 VAC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.20	Enclosure	Withdrawable Metal Clad, Compartmented	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.21	Degree of Protection by Enclosure	External: IP 42, Internal: IP 20, Internal partitions between functional units and shutters for bus bar & cable side: IP 4X	Confirmed	Ok	Ecternal:IP41 & other Confirmed	С	IP41	С
2.22	Installation	Floor Self-Standing, Side by Side	Confirmed	Ok	Floor Self-Standing, ACC to General Arrangement	OK	Confirmed	Ok
2.23	Rear / Front Access	Rear and Front Access	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.24	Top / Bottom Cable Entry	Cables: Bottom Entry	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.25	Sheet Steel Thickness, Frame & Walls	Minimum 2.5 mm	Minimum 2mm	Ok	Confirmed	Ok	Confirmed	Ok
2.26	Paint	Electrostatic Powder	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.27	Color Finish	RAL 7032	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.28	Routine Tests	Required (Withstand tests and reports as per IEC 62271-200 or IEC 298, IEC 60694, IPS-M-EL-144 (4) and Specification)	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok



#### احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره صفحه: ۱۴ از ۲۸

شماره پیمان:		TBE FOR EXISTENT MV SWITCHGEAR EXPANSION & RCP           نسخه سریال نوع مدر ک نوع مد									
•۵۳ - •۷۳ – ٩١٨۴	پروژه	بسته کاری	صادر كننده	تسهيلات	رشته	نوع مدرک	سر يال	نسخه			
$\omega_1 = v_{i1} = v_{iN1}$	ВК	GCS	PEDCO	120	EL	TBE	0003	D01			

#### TBE for 3.3 KV Switchgear (Starter Panel of Fire Water Pump) PMR for Existent MV Switchgear Expansion MR & RCP (BK-GCS-PEDCO-120-EL-MR-0003) **Purchaser Requirement** Pars Tableau Status **Runin Sanat Gostar Status Taban Tablo** Status Item **Description** Test certificates of the SWGR type as per 2.29 Type Tests IEC62271-200 or IEC 298, IEC60694, and Confirmed Ok Confirmed Ok Confirmed Ok IPS-M-EL-144 (4) 2.30 Overall Dimensions (HxWxD) [mm] Vendor to Advise According to Technical Offer Ok After Contract Ok Confirmed Ok 2.31 Total Weight [kg] Vendor to Advise According to Technical Offer Ok After Contract Ok Confirmed Ok Ok 2.32 Overall Dimensions of 1 Cubicle (HxWxD) Vendor to Advise According to Technical Offer Ok After Contract Confirmed Ok Dynamic Load of One Cubicle [kg] Ok Ok Ok 2.33 Vendor to Advise According to Technical Offer After Contract Confirmed 3. MV Circuit Breaker Manufacturer C 3.1 Vendor to Advise Hyundai/South Korea Ok Pars Switch Confirmed Ok 3.2 Standard IEC62271-100 Confirmed Ok Confirmed Ok Confirmed Ok Vacuum Confirmed Ok Confirmed Ok Ok 3.3 Type Confirmed 3.4 Fixed/ Withdrawable Withdrawable Confirmed Ok Confirmed Ok Confirmed Ok 3.5 Rated Voltage $3.3 \text{ kV} \pm 10 \%$ Confirmed Ok Confirmed Ok Confirmed Ok 3.6 Rated Frequency $50 \text{ Hz} \pm 5 \%$ Confirmed Ok Confirmed Ok Confirmed Ok Ok 3.7 No. Of Phases and Poles 3-Phase Confirmed Ok Confirmed Confirmed Ok Rated Insulation Levels between earth and phase 10 KV Confirmed • One Minute Power Frequency Withstand Voltage (RMS) 3.8 2 KV Confirmed Ok OK Confirmed Ok N.A • One Minute Power Frequency Withstand Voltage of Aux. Circuit (RMS) 40 KV Confirmed • Impulse Withstand Voltage (Peak) 3.9 Rated Normal Current 630 A Confirmed Ok Confirmed Ok Confirmed Ok 3.10 Rated Short Time Current 25 kA; 1 sec Confirmed Ok Confirmed Ok Confirmed Ok 3.11 Rated Peak Withstand Current 62.5 kA Confirmed Ok 63 KA Ok Confirmed Ok 3.12 Rated Short Circuit Breaking Current Vendor to Advise According to Catalogue Ok 25 KA Ok Ok Confirmed 3.13 Rated Short Circuit Making Current According to Catalogue Ok Ok Ok Vendor to Advise 63 KA Confirmed Ok 3.14 Acc. to IEC62271-100 Ok Ok Maximum Tolerable Temperature Rise Confirmed Confirmed Confirmed



# احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:			TBE FOR EXIS	STENT MV SWITCHGE	AR EXPANSION & R	CP		
۰۵۳ - ۰۷۳ — ۹۱۸۴	پروژه	بسته کاری	صادركننده	تسهيلات	رشته	نوع مدرک	سر يال	نسخه
ω· · · · · · · · · · · · · · · · · · ·	BK	GCS	PEDCO	120	EL	TBE	0003	D01

شماره صفحه: ۱۵٪ از ۲۸

TDE 101 3.3 IX V SWITCHEGAL (Starter Land of Fire Water Lump)	TBE for 3.3 KV Switchgean	r (Starter Panel of Fire Water Pump)
---	---------------------------	--------------------------------------

MR	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
Item	Description							
3.15	Design Temperature Rise	Acc. to IEC62271-100	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.16	Operating Mechanism	Motor & Hand operated Spring Charged Stored Energy Mechanism	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.17	Release Type	Shunt Trip	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.18	Rated Operating Sequence	O-0.3S-CO-3MIN-CO	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.19	Rated Voltage of Auxiliary Equipment	110V DC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.20	Rated Operating Voltage of Releases	110V DC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.21	Rated Operating Voltage of Charging Motors	110V DC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.22	Voltage Tolerances for Auxiliary Apparatus:     Trip Circuit     Close Circuit     Motor Running     Motor at the Instant of Start	70%-110% 85%-110% 85%-110% 70%-110%	Confirmed	Ok	After Contract	Ok	Confirmed	Ok
3.23	Power consumption of Auxiliary Apparatus:[W]  Trip Circuit Closed Circuit Charging motor Under voltage release Multifunction relay Transducers	110V DC  Vendor to Advise	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.24	<ul> <li>1 C.B. Open/Close Auxiliary Contacts:</li> <li>No. Of Make Contacts</li> <li>No. Of Break Contacts</li> <li>Rated Voltage</li> <li>Rated Current at 110V DC</li> <li>Breaking Current at 110V DC</li> </ul>	6 6 110V DC VTA VTA	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.25	Truck Position Auxiliary Contacts:  No of Make Contacts  No of Break Contacts  Rated Voltage  Rated Current at 110V DC  Breaking Current at 110V DC	1NO + 1NC 1NO + 1NC 110V DC VTA VTA	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.26	Routine Tests	IEC62271-100	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.27	Type Tests	IEC62271-100	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok



Highest System Voltage

#### نگهداشت و افزایش تولید میدان نفتی بینک سطح الارض

## احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک

نوع مدرك

TBE

سريال

0003

D01

Ok

Confirmed



شماره صفحه: ۱۶ از ۲۸

Ok

	شماره پیمان:	AR EXPANSION & RO	CP.				
۰۵۳ – ۳۷۰ – ۹۱۸۴		پروژه	بسته کاری	صادر کننده	تسهيلات	رشته	
- ωι - γι - γιχι		ВК	GCS	PEDCO	120	EL	

3.6 kV

		TBE for <u>3.3 KV</u> Sw	vitchgear (Starter Panel of	Fire Wat	er Pump)			
MR Item	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)  Description	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
4.1	Manufacturers Name	Vendor to Advise	Pars Shar/Iran	Ok	Pars Shar	Ok	Confirmed	Ok
4.2	Standard	IEC60044-2	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.3	Туре	Epoxy Cast Resin	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.4	Fixed Withdrawable	Withdrawable	Tilting	N	Confirmed	Ok	Confirmed	Ok
4.5	Highest System Voltage	3.6 kV	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.6	Rated Frequency	50 Hz	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.7	No. of Phase	Single Phase	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.8	Rated Primary Voltage [kV]	3.3/√3 kV	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.9	Rated Secondary Voltage [V]	110/√3 V	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.10	Rated Insulation Levels between earth and phase  One Minute Power Frequency Withstand Voltage (RMS)  One Minute Power Frequency Withstand Voltage of Aux. Circuit (RMS)  Impulse Withstand Voltage (Peak)	$10 \text{ kV} / \sqrt{3}$ $2 \text{ kV} / \sqrt{3}$ $40 \text{ kV} / \sqrt{3}$	Confirmed	Ok	Confirmed  N.A  Confirmed	Ok	Confirmed	Ok
4.11	System Earthing	TNS	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.12	Rated Voltage Factor	Vendor to Advise	According to Catalogue	Ok	After Contract	Ok	Confirmed	Ok
4.13	Rated Burden	Vendor to Advise	According to Catalogue	Ok	After Contract	Ok	Confirmed	Ok
4.14	Accuracy Class: • for Protection (with separate Winding) • for Measuring (with separate Winding)	CL. 3P 1.0	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.15	Insulation Class & Temperature Rise	Class E, Temp. Rise Class Y	Confirmed	Ok	Insulation (Class A)/ Temperature Rise (N.A)	С	Confirmed	Ok
5. N	IV Current Transformers				, , , , , , , , , , , , , , , , , , , ,			
5.1	Manufacturer's Name	Vendor to Advise	Pars Shar/Iran	Ok	Pars Shar	Ok	Confirmed	Ok
5.2	Standard	IEC60044-1	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
5.3	Туре	Dry Type	Confirmed	Ok	Resin Type	Ok	Confirmed	Ok

Confirmed

Ok

Confirmed



# احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:		AR EXPANSION & RO	CP					
۰۵۳ - ۰۷۳ - ۹۱۸۴	پروژه	بسته کاری	صادر کننده	تسهيلات	رشته	نوع مدرك	سريال	نسخه
$\omega_1 = \omega_1 = \omega_1$	ВК	GCS	PEDCO	120	EL	TBE	0003	D01

شماره صفحه: ۱۷ از ۲۸

	TBE for 3.3 KV Switchgear (Starter Panel of Fire Water Pump)											
MR Item	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003) Description	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status				
5.5	Rated Frequency	50 Hz	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
5.6	Rated Secondary Current	1 A / 5 A According to SLD	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
5.7	Rated Continuous Thermal Current	1.2 x Rated primary current	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
5.8	Rated Short Time, Current	25 kA, 1 Sec	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
5.9	Rated Dynamic Current	63 kA	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
5.10	Rated Burden	Vendor to Advise	According to Catalogue	Ok	After Contract	Ok	Confirmed	Ok				
5.11	Rated Transformation Ratio and No. of Cores	According to Single Line Diagram	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
5.12	Accuracy Class:  • Measuring  • Protection	Class 1: Class 1FS5 Class X: where required Class 5P20 protections	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
5.13	Routine Tests	IEC60044-1	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
5.14	Type Tests	IEC60044-1	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok				
5.15	Rated Insulation Levels between earth and phase  One Minute Power Frequency Withstand Voltage (RMS)  One Minute Power Frequency Withstand Voltage of Aux. Circuit (RMS)  Impulse Withstand Voltage (Peak)	$10 \text{ kV} / \sqrt{3}$ $2 \text{ kV} / \sqrt{3}$ $40 \text{ kV} / \sqrt{3}$	Confirmed	Ok	Confirmed  N.A  Confirmed	Ok	Confirmed	Ok				
6. E	arth Switch											
6.1	Manufacturer's Name	Vendor to Advise	Parstableau/Iran	Ok	Runin Sanat Gostar		Confirmed	Ok				
6.2	Manufacturer's Type Designation	Vendor to Advise	Manual	Ok	After Contract		Confirmed	Ok				
6.3	Standard	IEC62271-102	Confirmed	Ok	After Contract		Confirmed	Ok				
6.4	Туре	Make Proof	Confirmed	Ok	After Contract		Confirmed	Ok				
6.5	Number of Phase	3	Confirmed	Ok	After Contract		Confirmed	Ok				
6.6	Frequency	50 Hz	Confirmed	Ok	After Contract		Confirmed	Ok				
6.7	Rated Voltage	11 kV	Confirmed	Ok	After Contract		Confirmed	Ok				
6.8	Rated Lighting Impulse Withstand Voltage	75 kV	Confirmed	Ok	After Contract		Confirmed	Ok				



## احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:									
·۵۳ - ·۷۳ — ٩١٨۴	پروژه	بسته کاری	صادركننده	تسهيلات	رشته		سر يال	نسخه	
· ωι - · νι - ιικτ	BK.	GCS	PEDCO	120	FI	TRE	0003	D01	

شماره صفحه : ۱۸ از ۲۸

		TBE for <u>3.3 KV</u> Sw	vitchgear (Starter Panel o	f Fire Wat	er Pump)			
MR Item	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)  Description	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
6.9	Rated 1 Minute Power Frequency Voltage	28 kV	Confirmed	Ok	After Contract		Confirmed	Ok
6.10	Rated Short Time (1s) Current	25 kA	Confirmed	Ok	After Contract		Confirmed	Ok
6.11	Rated Peak Withstand Current	62.5 kA	Confirmed	Ok	After Contract		Confirmed	Ok
6.12	Rated Short Circuit Making Current	62.5 kA	Confirmed	Ok	After Contract		Confirmed	Ok
6.13	Actuation Mechanism	Pre-tension Spring	Confirmed	Ok	After Contract		Confirmed	Ok
6.14	No. of Auxiliary Contacts (Min.)	2NO + 2NC	Confirmed	Ok	After Contract		Confirmed	Ok
6.15	Aux. Contacts Rated Voltage	110V DC	Confirmed	Ok	After Contract		Confirmed	Ok
6.16	Aux. Contacts Rated Current	1A	Confirmed	Ok	After Contract		Confirmed	Ok
6.17	Interlocks	According (but not limited) to Appendix B of IPS-M-EL-144 (4) specifically:  To prevent closure of Earth Switch when CB is not in Test or withdraw position  To prevent Insertion of CB when Earth Switch is connected.  To prevent connection of Earth Switch when upstream Switch is not open i.e. electromagnetic coil (only for incoming)	Confirmed	Ok	After Contract		Confirmed	Ok
6.18	Routine Tests	IEC62271-102	Confirmed	Ok	After Contract		Confirmed	Ok
6.19	Type Tests (Certificates)	IEC62271-102	Confirmed	Ok	After Contract		Confirmed	Ok
7. M	Iotor Feeder Protection Relay					·		
7.1	Manufacturer's Name	Vendor to Advise	Schneider/France	Ok	Schneider		Confirmed	Ok
7.2	Manufacturer's Type Designation	Vendor to Advise	P3U20	Ok	ACC to Technical Proposal		Confirmed	Ok
7.3	Туре	Digital Multi-Function Relay + Display with adjustment Menu	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.4	Installation	Flush Mounted	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.5	Included Protection (ANSI Codes)	50, 51, 46, 50G, 51G, 86 (Separate Relay)	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.6	Rated Current [A]	5	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.7	Rated Frequency [Hz]	50 Hz	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok



# احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:			TBE FOR EXIS	STENT MV SWITCHGE	AR EXPANSION & RO	CP CP		
۰۵۳ - ۰۷۳ — ۹۱۸۴	پروژه	بسته کاری	صادركننده	تسهيلات	رشته	نوع مدرك	سر يال	نسخه
ωι	ВК	GCS	PEDCO	120	EL	TBE	0003	D01

شماره صفحه : ۱۹ از ۲۸

		TBE for 3.3 KV Sw	vitchgear (Starter Panel o	f Fire Wat	er Pump)			
MR	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
Item	Description							
7.8	Burden [VA]	Vendor to Advise	According to Catalogue	Ok	After Contract	Ok	Confirmed	Ok
7.9	Overload Capability Of Current Path	100xIn < 1 Sec.	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.10	Rated Voltage Auxiliary Voltage [V]	110V DC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.11	Auxiliary Voltage Permissible Range [V]	Min. ± 15% of Un	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.12	Power Consumption [W]	Vendor to Advise	Confirmed	Ok	After Contract	Ok	Confirmed	Ok
7.13	Trip Relay Contacts	2NO + 2NC at least	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.14	Alarm Relay Contacts	2NO + 2NC at least	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.15	Auxiliary Contacts Ratings  • Contacts Voltage Rating [V]  • Contacts Rated Continuous Current	110V DC Vendor to Advise	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.16	Ingress Protection	IP42	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.17	Routine Tests	IEC 255	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.18	Type Tests (Certificates)	IEC 255	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8. S <sub>I</sub>	oare Part					,		
8.1	Commissioning Spare Parts according to attach 22 of MR	Yes	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.2	Two year Operation Spare Parts according to attach 22 of MR	Yes	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok

#### **Status Legends:**

A=Acceptable

N=Not Acceptable

N/A=Not Applicable

INA=Information Not Available

C=Clarification is Required

CA= Conditionally Acceptable

M = Requirement is Mandatory



# احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:			TBE FOR EXIS	STENT MV SWITCHGE	AR EXPANSION & RO	CP		
۰۵۳ - ۲۷۳ – ۹۱۸۴	پروژه	بسته کاری	صادر كننده	تسهيلات	رشته	نوع مدرک	سر يال	نسخه
ω ( · · · · · · · · · · · · · · · · · ·	ВК	GCS	PEDCO	120	EL	TBE	0003	D01

شماره صفحه : ۲۰ از ۲۸

		TBE fo	or Remote Control Panel	(RCP)				
MR Item	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)  Description	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
1. E	nvironmental Conditions (Process Basis Design, B	K-GNRAL-PEDCO-000-PR-DB-0001)						
1.1	Location	Binak Oilfield in Bushehr Province	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.2	Max. Outdoor Ambient Temperature	52°C	Confirmed	Ok	40°C	С	Confirmed	Ok
1.3	Min. Outdoor Ambient Temperature	+5 °c	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.4	Direct Sunlight Temperature	85°C	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.5	Maximum Relative Outdoor Humidity	100%	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.6	Altitude	12.5 m Above Sea Level	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2. Ge	2. General Information							
2.1	Tag Numbers	RCP-02 (Indoor Safe)	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.2	Quantity	1 Set	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.3	Application Standard	IPS-E-EL-100 IPS-M-EL-161 IPS-M-EL-143(3)	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.4	Manufacturer	By Vendor	Confirmed	Ok	Runin Sanat Gostar	Ok	Confirmed	Ok
2.5	Related Document	Wiring Diagram for Remote Control Panel (RCP) "BK-GCS-PEDCO-120-EL-DG-0005"  Data Sheets for Remote Control Panel "BK-GCS-PEDCO-120-EL-DT-0015"	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3. El	ectrical Data							
3.1	System Voltage/ Frequency	400V AC / 50Hz	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.2	Voltage Variation/ Frequency Variation	±10 / ± 5%	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.3	Insulation Voltage	0.6/1KV	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.4	No. of Phases / Wires	1Ph+N+PE	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.5	Control Voltage	110 VDC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.6	Space Heater Voltage	230VAC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok



111P - 770 - 711F

#### نگهداشت و افزایش تولید میدان نفتی بینک سطح الارض

# احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:			TBE FOR EXIS	STENT MV SWITCHGE	AR EXPANSION & RO	CP		
ę	پروژه	بسته کاری	صادر کننده	تسهيلات	رشته	نوع مدرک	سر يال	نسخه
'	BK	GCS	PEDCO	120	EL	TBE	0003	D01

شماره صفحه : ۲۱ از ۲۸

		TBE fo	or <u>Remote Control Panel</u> (	(RCP)					
MR Item	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)  Description	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status	
3.7	Internal/ External Voltage Supply	External	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok	
3.8	Bus-Bars Material	Indoor: Heat Shrink Copper Outdoor: Silver Plated Copper	Confirmed	Ok	N.A	Ok	Confirmed	Ok	
4. Ei	nclosure Data								
4.1	Enclosure Type	Wall Mounted, Fixed Type, Front Access	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok	
4.2	Degree of Protection	Indoor: IP 42	Confirmed	Ok	Confirmed	Ok	IP41	С	
4.3	Cable Entry	Bottom via Gland	Confirmed	Ok	N.A	С	Confirmed	Ok	
4.4	Material	Painted Sheet Steel	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok	
4.5	Finish Color	RAL 7032	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok	
4.6	Dimensions (HxWxD)	By Vendor	Confirmed	Ok	After Contract	Ok	Confirmed	Ok	
4.7	Sheet Steel Thickness (Body/Frame)	Wall Mounted: 1.5mm/2mm	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok	
4.8	Painting	For Corrosive & Hot Atmosphere	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok	
4.9	Thickness	Min. 60μ	Confirmed	Ok	80~120	С	Confirmed	Ok	
4.10	Туре	Epoxy Powder Elector Static	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok	
4.11	Weight	By Vendor	Confirmed	Ok	After Contract	Ok	Confirmed	Ok	
5. Se	elector Switch								
5.1	Selector Pole	1	Confirmed	Ok	N.A	Ok	Confirmed	Ok	
5.2	Selector Position	Position "OPEN-OFF-CLOSE"	Confirmed	Ok	N.A	Ok	Confirmed	Ok	
5.3	Selector Type	Spring Return to Center	Confirmed	Ok	N.A	Ok	Confirmed	Ok	
6. La	6. Label								
6.1	Language	English	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok	
6.2	Material	Stainless Steel-Screwed/Reverted	Confirmed	Ok	Laminated Plastic & Sticky Type	N	Confirmed	Ok	
6.3	Main Label (Front / Back)	Engraved / Black Font-White Background	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok	



# شرکت تبدیتوایا<sup>ن</sup> HIRGAN ENERGY

## احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک

شماره پیمان: TBE FOR EXISTENT MV SWITCHGEAR EXPANSION & RCP بسته کاری صادر كننده نوع مدرك پروژه تسهيلات سريال 711P - 77. - 7A. BK GCS PEDCO 120 EL TBE 0003 D01

شماره صفحه : ۲۲ از ۲۸

		TBE f	or Remote Control Panel	(RCP)				
MR Item	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)  Description	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
	nel Wiring					l		
7.1	Manufacturer	By Vendor	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.2	Туре	CU/PVC/PVC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.3	Power Wire Color	By Vendor	Confirmed	Ok	Black	Ok	Confirmed	Ok
7.4	Signal Wire Color (Voltage Presence Indicator)	By Vendor	Confirmed	Ok	Black	Ok	Confirmed	Ok
8. Pa	nel Terminal							
8.1	Manufacturer	By Vendor	Confirmed	Ok	ARRD	Ok	Confirmed	Ok
8.2	Model NO.	By Vendor	Confirmed	Ok	RTP	Ok	Confirmed	Ok
8.3	Туре	Solderless Clamp Type-Flame Retardant	Confirmed	Ok	Screw Type was Considered	Ok	Confirmed	Ok
8.4	Rated Voltage	According to IEC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.5	Size	Min. 4sqmm	Confirmed	Ok	Min 2.5 sqmm	Ok	Confirmed	Ok
8.6	Color	Neutral (Blue) / PE (Green/ Yellow)	Confirmed	Ok	Grey was Considered for all Terminals	Ok	Confirmed	Ok
9. AC	CCESSORIES							
9.1	Door Key	Yes	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
9.2	Gland Plate (Undrilled)	Yes	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
9.3	Gland Plate Type (Normal/Non-Magnetic)	Normal	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
9.4	Terminal Lugs	Yes	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
9.5	Signal Lamp ( 110 VDC)	C.B. Closed : Red C.B. Opened : Green C.B Fault : Yellow	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
10. Sp	are Part							
10.1	Commissioning Spare Parts according to attach 22 of MR	Yes	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
10.2	Two year Operation Spare Parts according to attach 22 of MR	Yes	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok

**Status Legends:** 



# احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره صفحه : ۲۳ از ۲۸

سريال

0003

D01

شماره پیمان:			TBE FOR EXIS	STENT MV SWITCHGE	AR EXPANSION & RO	CP
۹۱۸۴ – ۲۷۰ – ۹۱۸۴	پروژه	بسته کاری	صادركننده	تسهيلات	رشته	نوع مدرك
W1 11 (17)	ВК	GCS	PEDCO	120	EL	TBE

A=Acceptable
N=Not Acceptable
N/A=Not Applicable
INA=Information Not Available
C=Clarification is Required
CA= Conditionally Acceptable

M = Requirement is Mandatory

		ТВ	E for MV Capacitor Bank	<u> </u>				
MR Item	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)  Description	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
	eneral Information							
1.1	Quantity	1 Set for Each Gas Compressor	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.2	Tag Numbers	CB01~ CB03	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.3	Applicable Standards	IEC 60831 IPS-M-EL-181(2) IPS-M-EL-144(4)	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
1.4	Manufacturer's Name	By Vendor	Confirmed	Ok	Runin Sanat Gostar	Ok	Confirmed	Ok
2. E	nvironmental Conditions (Process Basis Design, BK-	GNRAL-PEDCO-000-PR-DB-0001)						
2.1	Location	Binak Oilfield in Busheher Province	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.2	Hazardous Area Classification	Safe	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.3	Max. Outdoor Ambient Temperature	52°C	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.4	Minimum Indoor Ambient Temp.	+5°C	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.5	Related Document	Specification for Capacitor Bank BK-GNRAL-PEDCO-000-EL-SP-0012 Calculation Note for Capacitor Banks "BK-GCS-PEDCO-120-EL-CN-0011" Data Sheets for Capacitor Bank "BK-GCS-PEDCO-120-EL-DT-0007" Capacitor Banks Single Line Diagram "BK-GCS-PEDCO-120-EL-SL-0007"	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.6	Maximum Indoor Relative Humidity	100%	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.7	Altitude (Above Sea Level)	12.5 m	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok



# احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:											
·۵۳ - ·۷۳ — ٩١٨۴	پروژه	بسته کاری	صادر کننده	تسهيلات	رشته	نوع مدرك	سريال	نسخه			
- ω1 · · · · · · · · · · · · · · · · · ·	BK	GCS	PEDCO	120	EL	TBE	0003	D01			

شماره صفحه : ۲۴ از ۲۸

		TB	E for <u>MV Capacitor Bank</u>					
MR	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
Item	Description							
2.8	Seismic Factor	Zone 3	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
2.9	Installation	Indoor	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3. E	lectrical Data							
3.1	System Voltage	11KV AC ±10%	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.2	System Frequency	50 Hz ±5%	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.3	No. of Phases	3	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.4	Control Voltage	230 VAC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.5	Space Heater Voltage	230 VAC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.6	Bus-Bar Rated Current	630A	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.7	Short Time Withstand Current	25 kA, 1 Sec.	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.8	Bus-Bars Material	Heat Shrink Copper	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
3.9	Bus-Bars Joints	Silver Plated	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4. E	nclosure Data							
4.1	Enclosure Type	Cabinet Mounted Capacitor	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.2	Degree of Protection	IP 42	Confirmed	Ok	IP41	С	IP41	С
4.3	Cable Entry	Bottom (by Cable Gland)	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.4	Type & Size of Power Cable	According to "BK-GCS-PEDCO 120-EL-CN-0003" (3C×95mm <sup>1</sup> CU/XLPE/SWA/PVC )	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.5	Control Cable	2×(5C×2.5 mm¹) for Current & Voltage Sample	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.6	Material	Painted Sheet Steel	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.7	Color	RAL 7032	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
4.8	Dimensions (HxWxD)	By Vendor	Confirmed	Ok	After Contract	Ok	Confirmed	Ok
4.9	Sheet Steel Thickness	2mm/2.5mm	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok



# احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



شماره پیمان:	TBE FOR EXISTENT MV SWITCHGEAR EXPANSION & RCP									
۰۵۳ - ۰۷۳ – ۹۱۸۴	پروژه	بسته کاری	صادركننده	تسهيلات	رشته	نوع مدرک	سر يال	نسخه		
ω ( · · · · · · · · · · · · · · · · · ·	ВК	GCS	PEDCO	120	EL	TBE	0003	D01		

شماره صفحه : ۲۵ از ۲۸

TBE for MV Capacitor Bank										
MR Item	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)  Description	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status		
4.10	Weight	By Vendor	Confirmed	Ok	After Contract	Ok	Confirmed	Ok		
	apacitors					7.5				
5.1	Capacitor Manufacturer/Model No.	By Vendor	Confirmed	Ok	P.K.C	Ok	Confirmed	Ok		
5.2	Rating of Each Capacitor Bank	360 KVAR	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok		
5.3	Capacitor Bank Rated Current	By Vendor	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok		
5.4	Capacitor Bank Rated Voltage	12 KV	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok		
5.5	Capacitor Bank Connection Type	Star	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok		
5.6	Capacitor Bank Rated Capacitance (µF)	By Vendor	Confirmed	Ok	After Contract	Ok	Confirmed	Ok		
5.7	Capacitance Variation (µF/°C)	By Vendor	Confirmed	Ok	After Contract	Ok	Confirmed	Ok		
5.8	Capacitor Unit Rated Voltage	By Vendor	Confirmed	Ok	After Contract	Ok	Confirmed	Ok		
5.9	Capacitor Unit Temp. Category	-5/D	Confirmed	Ok	N.A	Ok	Confirmed	Ok		
5.10	Capacitor Unit Insulating medium	By Vendor	Confirmed	Ok	After Contract	Ok	Confirmed	Ok		
5.11	Capacitor Unit Electrode Material	By Vendor	Confirmed	Ok	After Contract	Ok	Confirmed	Ok		
5.12	Capacitor Unit Dielectric Material	By Vendor	Confirmed	Ok	After Contract	Ok	Confirmed	Ok		
5.13	Capacitor Unit Case Material	Aluminum	Confirmed	Ok	Metal Enclosed	Ok	Confirmed	Ok		
5.14	Capacitor Unit Discharge Resistor (Ω)	By Vendor	Confirmed	Ok	After Contract	Ok	Confirmed	Ok		
5.15	Capacitor Unit Discharge time (to 75V)	<10 Minutes	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok		
6. Ft	ises					•				
6.1	Manufacturer / type	By Vendor	Confirmed	Ok	AEG	Ok	Confirmed	Ok		
6.2	Rated Voltage	11 KV	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok		
6.3	Service Voltage	11 KV±10%	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok		
6.4	Rated Frequency	50Hz±5%	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok		



# احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک



ه پیمان:	شمار	TBE FOR EXISTENT MV SWITCHGEAR EXPANSION & RCP									
·۵۳ – ·۷۳ – ۹۱۸۴		پروژه	بسته کاری	صادركننده	تسهيلات	رشته	نوع مدرک	سر يال	نسخه		
ω ( · · · · · · · · · · · · · · · · · ·		BK	GCS	PEDCO	120	FI	TRF	0003	D01		

شماره صفحه : ۲۶ از ۲۸

		ТВ	E for MV Capacitor Bank	<u> </u>				
MR Item	PMR for Existent MV Switchgear Expansion & RCP (BK-GCS-PEDCO-120-EL-MR-0003)  Description	Purchaser Requirement	Pars Tableau	Status	Runin Sanat Gostar	Status	Taban Tablo	Status
7. In	coming Circuit Breaker							L
7.1	Manufacturer / Type	By Vendor	Confirmed	Ok	MV HRC Fuse was Considered for Incoming	Ok	Confirmed	Ok
7.2	Туре	VCS & HRC Fuse, Fixed Type	Confirmed	Ok	MV HRC Fuse was Considered for Incoming	Ok	Confirmed	Ok
7.3	Rated Current	630A	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.4	Rated Short Circuit Breaking Current	25 KA	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.5	Rated Insulation Voltage	12 KV AC	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.6	Service Voltage	11 KV	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
7.7	Internal Protections	49, 50, 51	Confirmed	Ok	N.A	Ok	Confirmed	C
7.8	Voltage Protection	110 DC	Confirmed	Ok	N.A	Ok	Confirmed	С
7.9	Trip and Status aux. switches	Yes	Confirmed	Ok	N.A	Ok	Confirmed	С
8. Ac	ccessories							
8.1	Panel Lighting & Space Heater with Thermostat	Yes	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.2	Door Key	Yes	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.3	Gland Plate	Yes	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.4	Terminal Lugs	Yes	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.5	Commissioning Spare Parts according to attach 22 of MR	Yes	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.6	Two year Operation Spare Parts according to attach 22 of MR	Yes	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.7	Routine Test	Witnessed and Report	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok
8.8	Type Test Certificate	Certificate	Confirmed	Ok	Confirmed	Ok	Confirmed	Ok

#### **Status Legends:**

A=Acceptable
N=Not Acceptable
N/A=Not Applicable



· 27 - · 77 - 9114

#### نگهداشت و افزایش تولید میدان نفتی بینک سطح الارض

# HIRGAN ENERGY

#### احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک

شماره پیمان:	TBE FOR EXISTENT MV SWITCHGEAR EXPANSION & RCP									
:	پروژه	بسته کاری	صادر کننده	تسهيلات	رشته	نوع مدرک	سر يال	نسخه		
	BK	GCS	PEDCO	120	EL	TBE	0003	D01		

شماره صفحه: ۲۷ از ۲۸

INA=Information Not Available C=Clarification is Required CA= Conditionally Acceptable M = Requirement is Mandatory

#### **Conclusion Table:**

Item	Equipment	PARS TABLEAU	RUNIN SANAT GOSTAR	TABAN TABLO
1	11 KV Switchgear	Acceptable	Acceptable	Acceptable
2	3.3 KV Switchgear	Acceptable	Acceptable	Acceptable
3	RCP Panel	Acceptable	Acceptable	Acceptable
4	MV Capacitor Bank	Acceptable	Acceptable	Acceptable

#### **Conclusion Note:**


#### **PARS TABLEAU**

- 1- This vendor has no deviation in deviation form.
- 2- For these brands of breaker, type test for switchgear shall be submitted.
- 3 Vendor did not issue any technical proposal for MV Capacitor Bank & RCP. Therefore these 2 items have not been studied. In deviation form shall fill it.
- 4- Vendor will supply MV voltage transformer in Tilting instead of withdrawable.
- 5- According to data sheet, the minimum thickness of sheet steel is 2.5 mm while vendor will supply minimum as 2 mm.

#### **RUNIN SANAT GOSTAR**

- 1- While the ingress protection (IP) of MV switchgear, RCP & Capacitor bank in project data sheet is IP42, but this vendor will supply IP41, according to item 5.1.5 of IPS-M-EL-144(4), IP41 is acceptable.
- 2- Adaptor will be supplied in both sides of 11 KV switchgear for connection new panels to existing panels. Therefore more space is required. However in "Electrical Equipment Arrangement Layout for Building (BK-GCS-PEDCO-120-EL-PY-0008)", adaptor is considered by contractor & in the case when there is no need after PO, it will be deleted.
- 3- Vendor will consider relay "P3M32" for differential protection "87M". this relay is low impedance.
- 4- According to "Existent MV Switchgear Expansion Single Line Diagram" & "Electrical Typical Schematic Diagrams for MV panel", there is withdrawable PT on 3.3 KV switchgear. Therefore a bus riser shall be considered while the number of 3.3 KV panel will be 2.
- 5- The maximum design temperature of MV switchgear is 40 °C.
- 6- According to MV switchgear data sheet, insulation class & temperature rise of Voltage Transformer shall be Class "E" & "Y" respectively but vendor will supply class "A" for temp rise omly.







شماره پیمان:	TBE FOR EXISTENT MV SWITCHGEAR EXPANSION & RCP									
۹۱۸۴ - ۲۰۰۰	پروژه	بسته کاری	صادر كننده	تسهيلات	رشته	نوع مدرك	سويال	نسخه		
. ωι – . γι (1λ1	BK	GCS	PEDCO	120	EL	TBE	0003	D01		

شماره صفحه: ۲۸ از ۲۸

#### **TABAN TABLO**

- 1- While the ingress protection (IP) of MV switchgear, RCP & Capacitor bank in project data sheet is IP42, but this vendor will supply IP41, according to item 5.1.5 of IPS-M-EL-144(4), IP41 is acceptable.
- 2- Vendor will provide MV circuit breaker in two alternatives "ABB" & "Pars Switch".
- 3- Adaptor will be supplied in both sides of 11 KV switchgear for connection new panels to existing panels. Therefore more space is required. However in "Electrical Equipment Arrangement Layout for Building (BK-GCS-PEDCO-120-EL-PY-0008)", adaptor is considered by contractor & therefore there is no concern.
- 4- Vendor will consider relay "EASERGY P3M32" for differential protection "87M". this relay is low impedance.
- 5- According to "Existent MV Switchgear Expansion Single Line Diagram" & "Electrical Typical Schematic Diagrams for MV panel", there is withdrawable PT on 3.3 KV switchgear. Therefore a bus riser shall be considered while the number of 3.3 KV panel will be 2.