

 NISOC	نگهداشت و افزایش تولید میدان نفتی بینک سطح الارض احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک							 شرکت توسعه و پترو ایران  	
	ELECTRICAL POWER & CONTROL CABLE SCHEDULE								
شماره پیمان: ۰۵۳ - ۰۷۳ - ۹۱۸۴	پروژه BK	بسته کاری GCS	صادر کننده PEDCO	تسهیلات 120	رشته EL	نوع مدرک LI	سریال 0002	نسخه D00	شماره صفحه: ۹ از ۹

طرح نگهداشت و افزایش تولید ۲۷ مخزن

ELECTRICAL POWER & CONTROL CABLE SCHEDULE

نگهداشت و افزایش تولید میدان نفتی بینک

D00	June.2022	IFC	H.Shakiba	M.Fakharian	M.Mehrshad	
Rev.	Date	Purpose of Issue / Status	Prepared by:	Checked by:	Approved by:	CLIENT Approval
Class: 2		CLIENT Doc. Number: F0Z-709067				
status: IDC: Inter-Discipline Check IFC: Issued For Comment IFA: Issued For Approval AFD: Approved For Design AFC: Approved For Construction AFP: Approved For Purchase AFQ: Approved For Quotation IFI: Issued For Information AB-R: As-Built for CLIENT Review AB-A: As-Built –Approved						



NISOC

نگهداشت و افزایش تولید میدان نفتی بینک
سطح الارض

احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک

ELECTRICAL POWER & CONTROL CABLE SCHEDULE



شماره پیمان:

۰۵۳ - ۰۷۳ - ۹۱۸۴

نسخه	سریال	نوع مدرک	رشته	تسهیلات	صادرکننده	بسته کاری	پروژه
D00	0002	LI	EL	120	PEDCO	GCS	BK

شماره صفحه: ۹ از ۲

REVISION RECORD SHEET

Page	D00	D01	D02	D03	D04
1	X				
2	X				
3	X				
4	X				
5	X				
6	X				
7	X				
8	X				
9	X				
10					
11					
12					
13					
14					
15					
16					
17					
18					
19					
20					
21					
22					
23					
24					
25					
26					
27					
28					
29					
30					
31					
32					
33					
34					
35					
36					
37					
38					
39					
40					
41					
42					
43					
44					
45					
46					
47					
48					
49					
50					

Page	D00	D01	D02	D03	D04
51					
52					
53					
54					
55					
56					
57					
58					
59					
60					
61					
62					
63					
64					
65					
66					
67					
68					
69					
70					
71					
72					
73					
74					
75					
76					
77					
78					
79					
80					
81					
82					
83					
84					
85					
86					
87					
88					
89					
90					
91					
92					
93					
94					
95					
96					
97					
98					
99					
100					



NISOC

نگهداشت و افزایش تولید میدان نفتی بینک
سطح الارض

احداث ردیف تراکم گاز در ایستگاه جمع آوری بینک

ELECTRICAL POWER & CONTROL CABLE SCHEDULE



شماره پیمان:

۰۵۳ - ۰۷۳ - ۹۱۸۴

پروژه

بسته کاری

صادر کننده

تسهیلات

رشته

نوع مدرک

سریال

نسخه

شماره صفحه: ۳ از ۹

BK

GCS

PEDCO

120

EL

LI

0002

D00

1. ELECTRICAL CABLE NUMBERING SYSTEM

XXX-XXXXX- XX- XX
1 2 3

(1) 1ST GROUP (EQUIPMENT NUMBER)

(2) 2ND GROUP (CABLE TYPE COMMODITY CODE):

HP: HIGH VOLTAGE POWER CABLE (20 KV & ABOVE)

MP: MEDIUM VOLTAGE POWER CABLE (6 KV & ABOVE)

LP: LOW VOLTAGE POWER CABLE (VOLTAGE LESS THAN 1KV)

SH: CABLE FOR MOTOR SPACE HEATER




CS: CABLE FOR LOCAL CONTROL STATION

CT: CURRENT CABLES

C: CONTROL CABLES

(3) SERIAL NO.

2. CABLE TYPE



MV Power Cables (Armoured)

(a) Cable Voltage

M1 11 kV

M2 3.3 kV

(b) Lead Cover Type

L With Lead cover

N Without Lead cover

(c) Number of Cores

1 Single Core

3 Multi Core

LV Power Cables

(a) Armour Type

A Armoured

U Un-Armoured

(b) Lead Cover type

L With Lead cover

N Without Lead cover

(c) Number of cores

1 to 5

(d) VFD Type

V VFD Cables

None None VFD Cables

Control Cables

(b) Armour Type

A Armoured

U Un-Armoured

(c) Lead Cover type

L With Lead cover

N Without Lead cover

(d) Number of cores

1 to 30

Notes:

1- The control cable of IRP Pump will be supplied by vendor

Reference documents are as below:

Area Electrical Cable Route & Section Layout of Well Pads (BK-SSGRL-PEDCO-110-EL-PY-0006)

Electrical Cable Route & Section Layout For Switchgear Building of Well Pads (BK-SSGRL-PEDCO-110-EL-PY-0007)

Item	Rev	Cable Tag No.	Service Voltage (KV)	Equipment Tag		Rating (KW)	Size	Cable Size (SQMM)				Length (m)	Cable Gland Size		O.D (mm)	Cable Type	Description
				From	To			Core	Phase	N	E		Source	Field			
124	D00	P-2202B-LP-B	0.4	GCS-400-NSWG-001B	P-2202B	1.1	3×4	3C	4	-	-	410	M20	M20	16.6	LAL3	Closed Drain Pump B
125	D00	P-2202B-C-01	0.4	GCS-400-NSWG-001B	P-2202B	-	3×2.5	3C	3	-	-	50	M20	M20	15.3	CAL3	IRP--ESD for Closed Drain Pump B
126	D00	P-2202B-C-02	0.4	GCS-400-NSWG-001B	P-2202B	-	12×2.5	12C	3	-	-	50	M25	M25	23.5	CAL12	IRP--DCS for Closed Drain Pump B
127	D00	P-2202B-C-03	0.4	GCS-400-NSWG-001B	P-2202B	-	10×2.5	10C	3	-	-	410	M25	M25	22.9	CAL10	LCS for Closed Drain Pump B
128	D00	P-2101A-LP-A	0.4	GCS-400-NSWG-001A	P-2101A	30	3×35	3C	35	-	-	225	M32	M32	28.6	LAL3	Slug Pump A
129	D00	P-2101A-C-01	0.4	GCS-400-NSWG-001A	P-2101A	-	3×2.5	3C	3	-	-	50	M20	M20	15.3	CAL3	IRP--ESD for Slug Pump A
130	D00	P-2101A-C-02	0.4	GCS-400-NSWG-001A	P-2101A	-	12×2.5	12C	3	-	-	50	M25	M25	23.5	CAL12	IRP--DCS for Slug Pump A
131	D00	P-2101A-C-03	0.4	GCS-400-NSWG-001A	P-2101A	-	10×2.5	10C	3	-	-	225	M25	M25	22.9	CAL10	LCS for Slug Pump A
132	D00	P-2101B-LP-B	0.4	GCS-400-NSWG-001B	P-2101B	30	3×35	3C	35	-	-	225	M32	M32	28.6	LAL3	Slug Pump B
133	D00	P-2101B-C-01	0.4	GCS-400-NSWG-001B	P-2101B	-	3×2.5	3C	3	-	-	50	M20	M20	15.3	CAL3	IRP--ESD for Slug Pump B
134	D00	P-2101B-C-02	0.4	GCS-400-NSWG-001B	P-2101B	-	12×2.5	12C	3	-	-	50	M25	M25	23.5	CAL12	IRP--DCS for Slug Pump B
135	D00	P-2101B-C-03	0.4	GCS-400-NSWG-001B	P-2101B	-	10×2.5	10C	3	-	-	225	M25	M25	22.9	CAL10	LCS for Slug Pump B
136	D00	P-2302A-LP-A	0.4	GCS-400-NSWG-001A	P-2302A	20	3×16	3C	16	-	-	175	M25	M25	22.2	LAN3	Fire Water Jockey Pump A
137	D00	P-2302B-LP-B	0.4	GCS-400-NSWG-001B	P-2302B	20	3×16	3C	16	-	-	175	M25	M25	22.2	LAN3	Fire Water Jockey Pump B
138	D00	P-2209-LP-01	0.4	GCS-400-NSWG-001A	P-2209	2.2	3×4	3C	4	-	-	100	M20	M20	16.6	LAN3	Potable Water Pump
139	D00	P-2209-C-01	0.4	GCS-400-NSWG-001A	P-2209	-	3×2.5	3C	3	-	-	50	M20	M20	15.3	CAN3	IRP--ESD for Potable Water Pump
140	D00	P-2209-C-02	0.4	GCS-400-NSWG-001A	P-2209	-	12×2.5	12C	3	-	-	50	M25	M25	23.5	CAN12	IRP--DCS for Potable Water Pump
141	D00	P-2209-C-03	0.4	GCS-400-NSWG-001A	P-2209	-	10×2.5	10C	3	-	-	410	M25	M25	22.9	CAN10	LCS for Potable Water Pump
142	D00	P-2206-LP-01	0.4	GCS-400-NSWG-001A	P-2206	2.2	3×4	3C	4	-	-	145	M20	M20	16.6	LAN3	Diesel Oil Pump
143	D00	P-2206-C-01	0.4	GCS-400-NSWG-001A	P-2206	-	3×2.5	3C	3	-	-	50	M20	M20	15.3	CAN3	IRP--ESD for Diesel Oil Pump
144	D00	P-2206-C-02	0.4	GCS-400-NSWG-001A	P-2206	-	12×2.5	12C	3	-	-	50	M25	M25	23.5	CAN12	IRP--DCS for Diesel Oil Pump
145	D00	P-2206-C-03	0.4	GCS-400-NSWG-001A	P-2206	-	10×2.5	10C	3	-	-	410	M25	M25	22.9	CAN10	LCS for Diesel Oil Pump
146	D00	P-2201A-LP-A	0.4	GCS-400-NSWG-001E	P-2201A	1.1	3×4	3C	4	-	-	430	M20	M20	16.6	LAN3	LP Flare K.O. Drum Pump A
147	D00	P-2201A-C-01	0.4	GCS-400-NSWG-001E	P-2201A	-	3×2.5	3C	3	-	-	50	M20	M20	15.3	CAN3	IRP--ESD for LP Flare K.O. Drum Pump A
148	D00	P-2201A-C-02	0.4	GCS-400-NSWG-001E	P-2201A	-	12×2.5	12C	3	-	-	50	M25	M25	23.5	CAN12	IRP--DCS for LP Flare K.O. Drum Pump A
149	D00	P-2201A-C-03	0.4	GCS-400-NSWG-001E	P-2201A	-	10×2.5	10C	3	-	-	410	M25	M25	22.9	CAN10	LCS for LP Flare K.O. Drum Pump A
150	D00	P-2201B-LP-B	0.4	GCS-400-NSWG-001E	P-2201B	1.1	3×4	3C	4	-	-	430	M20	M20	16.6	LAN3	LP Flare K.O. Drum Pump B
151	D00	P-2201B-C-01	0.4	GCS-400-NSWG-001E	P-2201B	-	3×2.5	3C	3	-	-	50	M20	M20	15.3	CAN3	IRP--ESD for LP Flare K.O. Drum Pump B
152	D00	P-2201B-C-02	0.4	GCS-400-NSWG-001E	P-2201B	-	12×2.5	12C	3	-	-	50	M25	M25	23.5	CAN12	IRP--DCS for LP Flare K.O. Drum Pump B
153	D00	P-2201B-C-03	0.4	GCS-400-NSWG-001E	P-2201B	-	10×2.5	10C	3	-	-	410	M25	M25	22.9	CAN10	LCS for LP Flare K.O. Drum Pump B
154	D00	P-2103A-LP-A	0.4	GCS-400-NSWG-001A	P-2103A	1.5	3×4	3C	4	-	-	360	M20	M20	16.6	LAL3	Glycol Transfer Pump A
155	D00	P-2103A-C-01	0.4	GCS-400-NSWG-001A	P-2103A	-	3×2.5	3C	3	-	-	50	M20	M20	15.3	CAL3	IRP--ESD for Glycol Transfer Pump A
156	D00	P-2103A-C-02	0.4	GCS-400-NSWG-001A	P-2103A	-	12×2.5	12C	3	-	-	50	M25	M25	23.5	CAL12	IRP--DCS for Glycol Transfer Pump A
157	D00	P-2103A-C-03	0.4	GCS-400-NSWG-001A	P-2103A	-	10×2.5	10C	3	-	-	410	M25	M25	22.9	CAL10	LCS for Glycol Transfer Pump A
158	D00	P-2103B-LP-B	0.4	GCS-400-NSWG-001B	P-2103B	1.5	3×4	3C	4	-	-	360	M20	M20	16.6	LAL3	Glycol Transfer Pump B
159	D00	P-2103B-C-01	0.4	GCS-400-NSWG-001B	P-2103B	-	3×2.5	3C	3	-	-	50	M20	M20	15.3	CAL3	IRP--ESD for Glycol Transfer Pump B
160	D00	P-2103B-C-02	0.4	GCS-400-NSWG-001B	P-2103B	-	12×2.5	12C	3	-	-	50	M25	M25	23.5	CAL12	IRP--DCS for Glycol Transfer Pump B
161	D00	P-2103B-C-03	0.4	GCS-400-NSWG-001B	P-2103B	-	10×2.5	10C	3	-	-	360	M25	M25	22.9	CAL10	LCS for Glycol Transfer Pump B
				CS-400-NSWG-001B	P-2102	1.1	3×4	3C	4	-	-	360	M20	M20	16.6	LAL3	Glycol Manual Pump
				CS-400-NSWG-001B	P-2104	1.1	3×4	3C	4	-	-	430	M20	M20	16.6	LAL3	Glycol Drain Pump
				CS-400-NSWG-001B	P-2104	-	3×2.5	3C	3	-	-	50	M20	M20	15.3	CAL3	IRP--ESD for Glycol Drain Pump



Item	Rev	Cable Tag No.	Service Voltage (KV)	Equipment Tag		Rating (KW)	Size	Cable Size (SQMM)				Length (m)	Cable Gland Size		O.D (mm)	Cable Type	Description
				From	To			Core	Phase	N	E		Source	Field			
165	D00	P-2104-C-02	0.4	GCS-400-NSWG-001B	P-2104	-	12×2.5	12C	3	-	-	50	M25	M25	23.5	CAL12	IRP--DCS for Glycol Drain Pump
166	D00	P-2104-C-03	0.4	GCS-400-NSWG-001B	P-2104	-	10×2.5	10C	3	-	-	430	M25	M25	22.9	CAL10	LCS for Glycol Drain Pump
167	D00	CR-01-LP-01	0.4	GCS-400-NSWG-001A	GCS-400-CR-01	10	3×70+35	4C	70	35	-	335	M50	M50	47.9	LAL4	Main Compressor Crane
168	D00	CR-02-LP-01	0.4	GCS-400-NSWG-001B	GCS-400-CR-02	5	4×16	4C	16	16	-	175	M25	M25	24.5	LAN4	Fire Water Pumps Crane
169	D00	NDB-01-LP-01	0.4	GCS-400-NSWG-001A	GCS-400-NDB-01	20	3×150+70	4C	150	70	-	330	M63	M63	64.8	LAL4	Process Area Normal Lighting Panel
170	D00	EDB-01-LP-01	0.4	GCS-400-NSWG-001E	GCS-400-EDB-01	10	3×70+35	4C	70	35	-	330	M50	M50	47.9	LAL4	Process Area Emergency Lighting Panel
171	D00	NDB-02-LP-01	0.4	GCS-400-NSWG-001B	GCS-400-NDB-02	10	4×35	4C	35	35	-	180	M32	M32	32.1	LAN4	Utility Area Normal Lighting Panel
172	D00	EDB-02-LP-01	0.4	GCS-400-NSWG-001E	GCS-400-EDB-02	5	4×16	4C	16	16	-	180	M25	M25	24.5	LAN4	Utility Area Emergency Lighting Panel
173	D00	WS-01-LP-01	0.4	GCS-400-NSWG-001A	GCS-400-WS-01	37	3×2×120+70	4C	120	70	-	350	M63	M63	59.3	LAL4	Welding Receptacle (3 Phase) (Process Area)
174	D00	WS-02-LP-01	0.4	GCS-400-NSWG-001B	GCS-400-WS-02	37	3×150+70	4C	150	70	-	200	M63	M63	64.8	LAN4	Welding Receptacle (3 Phase) (Utility Area)
175	D00	CP01-LP-01	0.4	GCS-400-NSWG-001A	GCS-400-CP01	5	4×16	4C	16	16	-	150	M25	M25	24.5	LAN4	Cathodic Protection Transformer Rectifier1
176	D00	CP02-LP-01	0.4	GCS-400-NSWG-001B	GCS-400-CP02	10	4×25	4C	25	25	-	150	M32	M32	28.4	LAN4	Cathodic Protection Transformer Rectifier2
177	D00	HVAC-LP-01	0.4	GCS-400-NSWG-001E	CTRL- HVAC	150	3×2×150+70	4C	150	120	-	50	M63	M63	64.8	LAN4	HVAC Panel for Control Room
178	D00	CHG-001-LP-A1	0.4	GCS-400-NSWG-001A	GCS-110-CHG-001	20	4×16	4C	16	16	-	50	M25	M25	24.5	LAN4	110VDC Charger 1
179	D00	FB1-LP-A1	0.11DC	GCS-110-CHG-001	Fuse Box 1	-	2×16	2C	16	-	-	20	M25	M25	21.2	LAN2	DC Charger Fuse Box 1
180	D00	BAT1-LP-A1	0.11DC	Fuse Box 1	Battery Bank 1	-	2×16	2C	16	-	-	20	M25	M25	21.2	LAN2	DC Charger Battery Bank 1
181	D00	CHG-002-LP-A2	0.4	GCS-400-NSWG-001E	GCS-110-CHG-002	20	4×16	4C	16	16	-	50	M25	M25	24.5	LAN4	110VDC Charger 2
182	D00	FB2-LP-A2	0.11DC	GCS-110-CHG-002	Fuse Box 2	-	2×16	2C	16	-	-	10	M25	M25	21.2	LAN2	DC Charger Fuse Box 2
183	D00	BAT2-LP-A2	0.11DC	Fuse Box 2	Battery Bank 2	-	2×16	2C	16	-	-	10	M25	M25	21.2	LAN2	DC Charger Battery Bank 2
184	D00	CHG-002-LP-A3	0.4	GCS-400-NSWG-001A	GCS-24-CHG-001	13	4×6	4C	6	6	-	50	M25	M25	19.7	LAN4	24VDC Charger 1
185	D00	FB1-LP-A3	0.24DC	GCS-110-CHG-001	Fuse Box 1	-	2×10	2C	10	-	-	10	M25	M25	19.8	LAN2	DC Charger Fuse Box 1
186	D00	BAT2-LP-A3	0.24DC	Fuse Box 1	Battery Bank 1	-	2×10	2C	10	-	-	10	M25	M25	19.8	LAN2	DC Charger Battery Bank 1
187	D00	CHG-002-LP-A4	0.4	GCS-400-NSWG-001E	GCS-24-CHG-002	13	4×6	4C	6	6	-	50	M25	M25	19.7	LAN4	24VDC Charger 2
188	D00	FB2-LP-A4	0.24DC	GCS-24-CHG-002	Fuse Box 2	-	2×10	2C	10	-	-	10	M25	M25	19.8	LAN2	DC Charger Fuse Box 2
189	D00	BAT2-LP-A4	0.24DC	Fuse Box 2	Battery Bank 2	-	2×10	2C	10	-	-	10	M25	M25	19.8	LAN2	DC Charger Battery Bank 2
190	D00	UPS-001-LP-A5	0.4	GCS-400-NSWG-001A	GCS-110-UPS-001	49	3×70+35	4C	70	35	-	50	M50	M50	47.9	LAN4	110VAC UPS 1
191	D00	FB1-LP-A5	0.11AC	GCS-110-UPS-001	Fuse Box 1	-	2×50	2C	50	-	-	20	M32	M32	30.2	LAN2	UPS Fuse Box 1
192	D00	BAT2-LP-A5	0.11AC	Fuse Box 1	Battery Bank 1	-	2×50	2C	50	-	-	20	M32	M32	30.2	LAN2	UPS Battery Bank 1
193	D00	UPS-002-LP-A6	0.4	GCS-400-NSWG-001E	GCS-110-UPS-002	49	3×70+35	4C	70	35	-	50	M50	M50	47.9	LAN4	110VAC UPS 2
194	D00	FB2-LP-A6	0.11AC	GCS-110-UPS-002	Fuse Box 2	-	2×50	2C	50	-	-	20	M32	M32	30.2	LAN2	UPS Fuse Box 2
195	D00	BAT2-LP-A6	0.11AC	Fuse Box 2	Battery Bank 2	-	2×50	2C	50	-	-	20	M32	M32	30.2	LAN2	UPS Battery Bank 2
196	D00	UPS-Bypass-LP-01	0.4	GCS-400-NSWG-001E	GCS-110-UPS-Bypass	20	4×10	4C	10	10	-	50	M25	M25	22.1	LAN4	110VAC UPS By Pass
197	D00	Non UPS-LP-01	0.4	GCS-400-NSWG-001E	GCS-400-Non UPS	8	4×6	4C	6	6	-	50	M25	M25	19.7	LAN4	Non-UPS Load for Instrument
198	D00	NDB-CAP--LP-01	0.4	GCS-400-NSWG-001B	GCS-400-NDB-CAP	5	4×4	4C	4	4	-	20	M20	M20	17.7	LAN4	Capacitor Room Normal Lighting Panel
199	D00	MOV 1-LP-01	0.4	GCS-400-NSWG-001A		2	4×6	4C	6	6	-	175	M25	M25	19.7	LAN4	MOV 1
200	D00	FDP 01-LP-01	0.4	GCS-400-NSWG-001E	GCS-230-FDP 01	2	4×6	4C	6	6	-	175	M25	M25	19.7	LAN4	Fire Diesel Panel 01
201	D00	FDP 02-LP-02	0.4	GCS-400-NSWG-001E	GCS-230-FDP 02	2	4×6	4C	6	6	-	175	M25	M25	19.7	LAN4	Fire Diesel Panel 02
202	D00	SPH-01-LP-01	0.4	GCS-400-NSWG-001E	SPH-01	2	4×4	4C	4	4	-	30	M20	M20	17.7	LAN4	Space Heater & Lighting for New LV Switchgear
				CS-400-NSWG-001E	SPH-02	2	4×4	4C	4	4	-	30	M20	M20	17.7	LAN4	Space Heater & Lighting for MV Switchgear
				CS-400-NSWG-001B	GCS-400-NDP-CRM	30	4×25	4C	25	25	-	50	M32	M32	28.4	LAN4	Control Room Normal Lighting Panel
				CS-400-NSWG-001E	GCS-400-EDP-CRM	15	4×16	4C	16	16	-	50	M25	M25	24.5	LAN4	Control Room Emergency Lighting Panel



Item	Rev	Cable Tag No.	Service Voltage (KV)	Equipment Tag		Rating (KW)	Size	Cable Size (SQMM)				Length (m)	Cable Gland Size		O.D (mm)	Cable Type	Description
				From	To			Core	Phase	N	E		Source	Field			
206	D00	EDB-CAP-LP-01	0.4	GCS-400-NSWG-001E	GCS-400-EDB-CAP	5	4×4	4C	4	4	-	20	M20	M20	17.7	LAN4	Capacitor Room Emergency Lighting Panel
207	D00	LV-HVAC01-LP-01	0.4	GCS-400-NSWG-001A	LV-HVAC01	7	4×6	4C	6	6	-	50	M25	M25	19.7	LAN4	Split Feeder (HVAC Feeder-01 for LV Room)
208	D00	LV-HVAC02-LP-02	0.4	GCS-400-NSWG-001B	LV-HVAC02	7	4×6	4C	6	6	-	50	M25	M25	19.7	LAN4	Split Feeder (HVAC Feeder-02 for LV Room)
209	D00	MV-HVAC01-LP-01	0.4	GCS-400-NSWG-001A	MV-HVAC01	7	4×4	4C	4	4	-	10	M20	M20	17.7	LAN4	Split Feeder (HVAC Feeder-01 for MV Room)
210	D00	MV-HVAC02-LP-01	0.4	GCS-400-NSWG-001B	MV-HVAC02	7	4×4	4C	4	4	-	10	M20	M20	17.7	LAN4	Split Feeder (HVAC Feeder-02 for MV Room)
211	D00	HVAC01-LP-01	0.4	GCS-400-NSWG-001A	CAP-HVAC01	5	4×4	4C	4	4	-	20	M20	M20	17.7	LAN4	Split Feeder (HVAC Feeder-01 for Capacitor Room)
212	D00	HVAC02-LP-02	0.4	GCS-400-NSWG-001B	CAP-HVAC02	5	4×4	4C	4	4	-	20	M20	M20	17.7	LAN4	Split Feeder (HVAC Feeder-02 for Capacitor Room)
213	D00	CAP-01-LP-01A	0.4	GCS-400-NSWG-001A	CAP-01	100	3×120	3C	120			20	M50	M50	45.8	LN3	Capacitor Bank 1
214	D00	CAP-01-LP-01B	0.4	GCS-400-NSWG-001A	CAP-01	100	3×120	3C	120			20	M50	M50	45.8	LN3	Capacitor Bank 1
215	D00	CAP-02-LP-02A	0.4	GCS-400-NSWG-001B	CAP-02	100	3×120	3C	120			20	M50	M50	45.8	LN3	Capacitor Bank 2
216	D00	CAP-02-LP-02B	0.4	GCS-400-NSWG-001B	CAP-02	100	3×120	3C	120			20	M50	M50	45.8	LN3	Capacitor Bank 2

